

# AN96A07K


## Dynamic Focus Controller IC for CRT Monitor

### ■ Overview


The AN96A07K is a dynamic astigmatism and focus (DAF)IC for CRT monitor. It outputs parabola waves for focus control.

### ■ Features

- $f_H = 15$  to  $90\text{kHz}$ ,  $f_V = 50$  to  $120\text{Hz}$
- Constant-amplitude parabola-wave output following input frequency
- Coefficient of parabola-wave is controlled by an external resistor



### ■ Block Diagram



### ■ Pin Descriptions

Pin No.	Pin name	Pin No.	Pin name
1	GND	15	GND
2	Reference bias output (6V)	16	Ver. parabola output
3	Hor. sampling pulse input	17	Holding
4	Hor. phase shift pulse input	18	Ver. system reference bias output (2V)
5	V <sub>CC1</sub> (12V)	19	Triangular waveform generation capacitor
6	Holding	20	Oscillation prevention capacitor
7	Hor. system reference bias output (2V)	21	Oscillation prevention capacitor
8	Triangular waveform generation capacitor	22	Ver. parabola output amplitude adj.
9	Oscillation prevention capacitor	23	Feedback input
10	Oscillation prevention capacitor	24	Feedback output
11	Hor. parabola output amplitude adj.	25	V <sub>CC2</sub> (12V)
12	Feedback input	26	Ver. phase shift pulse input
13	Feedback output	27	Ver. sampling pulse input
14	Hor. parabola output	28	Reference bias output (4V)

### ■ Absolute Maximum Ratings

Parameter	Symbol	Rating	Unit
Supply voltage	V <sub>CC</sub>	13.4	V
Supply current	I <sub>CC</sub>	30	mA
Power dissipation <sup>Note 2)</sup>	P <sub>D</sub>	402	mW
Operating ambient temperature <sup>Note 1)</sup>	T <sub>opr</sub>	- 20 to + 75	°C
Storage temperature <sup>Note 1)</sup>	T <sub>stg</sub>	- 55 to + 150	°C

Note 1) Ta= 25°C except operating ambient temperature and storage temperature.

Note 2) Allowable power dissipation of the package at Ta=75°C.

### ■ Recommended Operating Range (Ta= 25°C)

Parameter	Symbol	Range
Operating supply voltage range	V <sub>CC</sub>	9.6V to 13.2V

### ■ Electrical Characteristics ( $T_a=25\pm2^{\circ}\text{C}$ )

Parameter	Symbol	Condition	min	typ	max	Unit
Circuit current	$I_{CC}$		14	19	24	mA
Circuit voltage	$V_{2-1.15}$		5.7	6.2	6.7	V
Circuit voltage	$V_{28-1.15}$		3.7	4.2	4.7	V
Circuit voltage	$V_{7-1.15}$		1.4	1.9	2.4	V
Circuit voltage	$V_{18-1.15}$		1.4	1.9	2.4	V
Hold charging current (1)	$I_{6(C)}$		-450	-370	-290	$\mu\text{A}$
Hold charging current (2)	$I_{17(C)}$		-450	-370	-290	$\mu\text{A}$
Hold discharging current (1)	$I_{6(D)}$		290	370	450	$\mu\text{A}$
Hold discharging current (2)	$I_{17(D)}$		290	370	450	$\mu\text{A}$
Hold leak voltage (1)	$I_{6(L)}$		-1.0	—	+1.0	$\mu\text{A}$
Hold leak voltage (2)	$I_{17(L)}$		-1.0	—	+1.0	$\mu\text{A}$
Triangular wave output voltage (1)	$V_{8-7}$		—	—	0.2	V
Triangular wave output voltage (2)	$V_{19-18}$		—	—	0.2	V
Triangular wave charging current (1)	$I_{8(C1)}$		-28	-20	-12	$\mu\text{A}$
Triangular wave charging current (2)	$I_{19(C1)}$		-28	-20	-12	$\mu\text{A}$
Triangular wave charging current (3)	$I_{8(C2)}$		-165	-135	-105	$\mu\text{A}$
Triangular wave charging current (4)	$I_{19(C2)}$		-165	-135	-105	$\mu\text{A}$
Triangular wave linearity (1)	$\Delta I_{8(R)}$		-3	0	+3	$\mu\text{A}$
Triangular wave linearity (2)	$\Delta I_{19(R)}$		-3	0	+3	$\mu\text{A}$
Triangular wave discharging current (1)	$I_{8(D)}$		7.0	8.5	9.5	mA
Triangular wave discharging current (2)	$I_{19(D)}$		7.0	8.5	9.5	mA
Parabola output voltage (1)	$V_{14(1)}$		3.7	4.2	4.7	V
Parabola output voltage (2)	$V_{14(2)}$		8.0	9.5	11.0	V
Parabola output voltage (3)	$\Delta V_{14(3)}$		-0.3	0	+0.3	V
Parabola output voltage (4)	$\Delta V_{14(4)}$		-4.5	-3.5	-2.5	V
Parabola output voltage (5)	$V_{16(5)}$		3.7	4.2	4.7	V
Parabola output voltage (6)	$V_{16(6)}$		8.0	9.5	11.0	V
Parabola output voltage (7)	$\Delta V_{16(7)}$		-0.3	0	+0.3	V
Parabola output voltage (8)	$\Delta V_{16(8)}$		-4.5	-3.5	-2.5	V
Clamp output voltage (1)	$V_{14(CL)}$		10.2	10.7	11.2	V
Clamp output voltage (2)	$V_{16(CL)}$		10.2	10.7	11.2	V
Horizontal operation frequency (max.)	$f_{H(\text{max.})}$	Operable upper limit frequency	—	(100)	—	kHz
Vertical operation frequency (max.)	$f_{V(\text{max.})}$	Operable upper limit frequency	—	(150)	—	Hz
Horizontal triangular wave output amplitude	$e_1$	$f_H=15 \text{ to } 90\text{kHz}$	—	(4)	—	$V_{P-P}$
Vertical triangular wave output amplitude	$e_2$	$f_V=50 \text{ to } 120\text{Hz}$	—	(4)	—	$V_{P-P}$
Horizontal parabola wave output amplitude	$e_3$	$f_H=64\text{kHz}$ $I_{11}=-20\mu\text{A}$	—	(4)	—	$V_{P-P}$
Vertical parabola wave output amplitude	$e_4$	$f_V=90\text{Hz}$ $I_{22}=-20\mu\text{A}$	—	(4)	—	$V_{P-P}$
Parabola wave exponential coefficient (horizontal)	$\alpha_H$	10k $\Omega$ between Pin12 to 13 10k $\Omega$ between Pin12 to 28	—	(2)	—	—
Parabola wave exponential coefficient (vertical)	$\alpha_V$	10k $\Omega$ between Pin23 to 24 10k $\Omega$ between Pin23 to 28	—	(2)	—	—

Note) The value in the above characteristics is not a guaranteed value, but reference one on design.










**Table 1**

No.	Parameter	Symbol	Measure- ment pin No.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28
1	Circuit current	I <sub>CC</sub>	5	0V	0V	0V	12V	0V					0V															to 5	0V	0V	
2	Circuit voltage	V <sub>2-1,15</sub>	2	0V	0V	0V	0V	12V	0V				0V															to 5	0V	0V	
3	Circuit voltage	V <sub>28-11,5</sub>	28	0V	0V	0V	0V	12V	0V				0V															to 5	0V	0V	
4	Circuit voltage	V <sub>7-1,15</sub>	7	0V	0V	0V	0V	12V	0V				0V															to 5	0V	0V	
5	Circuit voltage	V <sub>18-1,15</sub>	18	0V	0V	0V	0V	12V	0V				0V															to 5	0V	0V	
6	Hold charging current (1)	I <sub>6(C)</sub>	6	0V	2.5V	0V	12V	6V	5.7V				0V														to 5	0V	to 3		
7	Hold charging current (2)	I <sub>17(C)</sub>	17	0V	2.5V	0V	12V	6V	5.7V				0V														to 5	0V	to 3		
8	Hold discharging current (1)	I <sub>6(D)</sub>	6	0V	2.5V	0V	12V	6V	6.7V				0V														to 5	0V	to 3		
9	Hold discharging current (2)	I <sub>17(D)</sub>	17	0V	2.5V	0V	12V	6V	6.7V				0V														to 5	0V	to 3		
10	Hold leak current (1)	I <sub>6(L)</sub>	6	0V	0V	0V	12V	11V	6.7V				0V														to 5	0V	to 3		
11	Hold leak current (2)	I <sub>17(L)</sub>	17	0V	0V	0V	12V	11V	6.7V				0V														to 5	0V	to 3		
12	Triangle waveform output voltage (1)	V <sub>8-7</sub>	8	0V	0V	0V	2.5V	12V	11V				0V														to 5	0V	to 3		
13	Triangle waveform output voltage (2)	V <sub>19-18</sub>	19	0V	0V	0V	2.5V	12V	11V				0V														to 5	0V	to 3		
14	Triangle waveform changing current (1)	I <sub>8(Cl)</sub>	8	0V	0V	0V	12V	3V	4V				0V														to 5	0V	to 3		
15	Triangle waveform changing current (2)	I <sub>19(Cl)</sub>	19	0V	0V	0V	12V	3V	4V				0V														to 5	0V	to 3		
16	Triangle waveform changing current (3)	I <sub>8(Cz)</sub>	8	0V	0V	0V	12V	11V	4V				0V														to 5	0V	to 3		
17	Triangle waveform changing current (4)	I <sub>19(Cz)</sub>	19	0V	0V	0V	12V	11V	4V				0V														to 5	0V	to 3		
18	Triangle waveform linearity (1)	ΔI <sub>8(kt)</sub>	8	0V	0V	0V	12V	6V	2V ↓ 6V				0V													to 5	0V	to 3			
19	Triangle waveform linearity (2)	ΔI <sub>19(kR)</sub>	19	0V	0V	0V	12V	6V				0V														to 5	0V	to 3			

Table 1 (cont.)

No.	Parameter	Symbol	Measure- ment pin No.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	Pin No.
20	Triangle waveform discharging current (1)	$I_{8(D)}$	8	0V	0V	2.5V	12V	6V	$180\Omega$ to 1	6V			0V	6V	6V														to 5	to 4	to 3	
21	Triangle waveform discharging current (2)	$I_{9(D)}$	19	0V	0V	2.5V	12V	6V	6V				0V	6V	$180\Omega$ to 1	6V													to 5	to 4	to 3	
22	Parabola output voltage (1)	$V_{14(1)}$	14	0V	0V	0V	12V	0V	0 $\mu$ A		-20 $\mu$ A to 28 to 12	10k	0V	0V														to 5	0V	0V		
23	Parabola output voltage (2)	$V_{14(2)}$	14	0V	0V	0V	12V	0V	100 $\mu$ A		-20 $\mu$ A to 28 to 12	10k	0V	0V														to 5	0V	0V		
24	Parabola output voltage (3)	$\Delta V_{14(3)}$	14	0V	0V	0V	12V	0V	100 $\mu$ A ↓ -100 $\mu$ A		-20 $\mu$ A to 28 to 12	10k	0V	0V														to 5	0V	0V		
25	Parabola output voltage (4)	$\Delta V_{14(4)}$	14	0V	0V	0V	12V	0V	100 $\mu$ A		-20 $\mu$ A -150 $\mu$ A	10k	0V	0V													to 5	0V	0V			
26	Parabola output voltage (5)	$V_{16(5)}$	16	0V	0V	0V	12V	0V				0V	0V	0V	0 $\mu$ A													to 5	0V	0V		
27	Parabola output voltage (6)	$V_{16(6)}$	16	0V	0V	0V	12V	0V				0V	0V	0V	0 $\mu$ A													to 5	0V	0V		
28	Parabola output voltage (7)	$\Delta V_{16(7)}$	16	0V	0V	0V	12V	0V				0V	0V	0V	0 $\mu$ A													to 5	0V	0V		
29	Parabola output voltage (8)	$\Delta V_{16(8)}$	16	0V	0V	0V	12V	0V				0V	0V	0V	0 $\mu$ A													to 5	0V	0V		
30	Clamp output voltage (1)	$V_{14(CL)}$	14	0V	0V	2.5V	12V	0V	0 $\mu$ A		-20 $\mu$ A to 28 to 12	10k	0V	0V													to 5	0V	0V			
31	Clamp output voltage (2)	$V_{16(CL)}$	16	0V	0V	2.5V	12V	0V				0V	0V	0V	0 $\mu$ A												to 5	0V	0V			











### ■ Pin Descriptions

Pin No.	Pin name	Waveform	Equivalent circuit	Function
1	GND	0V		GND for horizontal system
2	Reference bias output (6V)	DC (6.0V)		Reference bias output (6V)
3	Hor. sampling pulse input			Input of sampling pulse (0.1 to 0.2μs) for detecting triangular waveform amplitude
4	Hor. phase shift pulse input			Pulse input (0.5 to 2μs) for discharging triangular waveform voltage
5	V <sub>CC1</sub> (12V)	12V		Power supply for horizontal system
6	Holding	Smoothed voltage (3 to 11V) Dynamically variable		Determines the charging current of triangular waveform. Dynamically variable with f <sub>M</sub> .
7	Hor. system reference bias output (2V)	DC (2.0V)		Reference bias for horizontal system (2V)
8	Triangular waveform generation capacitor			Triangular waveform generation capacitor The discharging current of triangular waveform sinks into the 2V-reference-voltage source (Pin7).









## ■ Pin Descriptions (cont.)

Pin No.	Pin name	Waveform	Equivalent circuit	Function
9	Oscillation prevention capacitor	4V		Oscillation prevention capacitor If the parabola output oscillates, a capacitor of several 10pF must be connected between this pin and Pin10.
10	Oscillation prevention capacitor			Oscillation prevention capacitor If the parabola output oscillates, capacitor of several 10 pF must be connected between this pin and Pin9.
11	Hor. parabola output amplitude adjustment	DC (11.2V)		Control pin of the amplitude of horizontal parabola output. If the current is increased by inserting a resistor between this pin and GND, the amplitude decrease.
12	Feedback input			Feedback input for gain adjustment
13	Feedback output			Feedback output-pin for gain adjustment The gain is set by a resistor which is connected between Pins12 and 28.
14	Hor. parabola output			Output of horizontal parabola waveform
15	GND	0V		GND for vertical system


## ■ Pin Descriptions (cont.)

Pin No.	Pin name	Waveform	Equivalent circuit	Function
16	Ver. parabola output			Output of vertical parabola waveform
17	Holding	 Smoothed voltage (3 to 11V) Dynamically variable		Control pin of the charging current of vertical-system triangular-waveform Dynamically changable with $f_v$ .
18	Ver. system reference bias output	DC (2.0V)		Reference bias of vertical system (2V)
19	Triangular generation capacitor			Triangular waveform-generation capacitor The discharging current of triangular waveform sinks into the 2V reference voltage source (Pin18).
20	Oscillation prevention capacitor			Oscillation-prevention capacitor If the parabola output oscillates, a capacitor of several 10pF must be connected between this pin and Pin21.
21	Oscillation prevention capacitor			Oscillation-prevention capacitor If the parabola output oscillates, a capacitor of several 10pF must be connected between this pin and Pin20.

## ■ Pin Descriptions (cont.)

Pin No.	Pin name	Waveform	Equivalent circuit	Function
22	Ver. parabola output amplitude adj.	DC (11.2V)		Control pin of the amplitude of vertical parabola output When the current is increased by inserting a resistor between this pin and GND, the amplitude decrease.
23	Feedback input			Feedback input for gain adjustment
24	Feedback output			Feedback output for gain adjustment The gain is set by the value of a resistor which is connected between Pins 23 and 28.
25	V <sub>CC2</sub> (12V)	12V		Ver. system power supply
26	Ver. phase shift pulse input			Pulse (200 to 700μs) input for discharging triangular waveform
27	Ver. Sampling pulse input			Input of sampling pulse (50 to 80μs) which detects the amplitude of triangular waveform
28	Reference bias output (4V)	DC (4.0V)		Output for reference bias (4V)

### ■ Application Circuit



**Request for your special attention and precautions in using the technical information and semiconductors described in this book**

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances). Consult our sales staff in advance for information on the following applications:
- Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
- Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.