

8T20 Multivibrator

Bidirectional One-Shot Product Specification

Logic Products

FEATURES

- Differential Input Threshold = $\pm 4\text{mV}$
- Pulse Position Error = Typically $< 3\text{ns}$
- Max. Input Frequency = 8MHz
- Triggers on Positive and/or Transitions

APPLICATIONS

- Disc, Tape and Drum Readers
- Digital Communications Receivers
- Signal Conditioners
- Transition Detectors

DESCRIPTION

The Bidirectional One Shot is intended for applications where high speed low level signal processing is required.

The 8T20 is a Monolithic Building Block, consisting of a high speed analog comparator, digital control circuitry, and a precision monostable multivibrator. The differential input threshold voltage is be-

TYPE	TYPICAL PROPAGATION DELAY	TYPICAL SUPPLY CURRENT (TOTAL)
N8T20	30ns	

ORDERING CODE

PACKAGES	COMMERCIAL RANGE $V_{CC} = 5V \pm 5\%$; $T_A = 0^\circ\text{C}$ to $+70^\circ\text{C}$
Plastic DIP	N8T20N

NOTE:

For information regarding devices processed to Military Specifications, see the Signetics Military Products Data Manual.

INPUT AND OUTPUT LOADING AND FAN-OUT TABLE

PINS	DESCRIPTION	8T
PEC, NEC	Input	1ul
MR	Input	1ul
A, A; Q, Q	Output	10ul


NOTE:

A unit load (ul) is $40\mu\text{A } I_{IH}$ and $-1.6\text{mA } I_{IL}$.


tween $\pm 4\text{mV}$ with respect to the input reference level which may range from -3.2V to $+4.2\text{V}$. For input frequencies up to 8MHz , the device may be condi-

tioned to act as a frequency doubler since it can trigger on both positive and negative input transitions.


PIN CONFIGURATION



LOGIC SYMBOL




LOGIC SYMBOL (IEEE/IEC)



Multivibrator

8T20

LOGIC DIAGRAM



Timing pins permit using this device in a variety of applications where external control over pulse width is desirable. Pulse width (t^W) is defined by the relationship $t^W = C_X R_X$. Loge 2. Pulse width stability is internally compensated and virtually independent of temperature and V^{CC} variations, thus only limited by the accuracy of external timing components.

An internal resistive divider is available on the chip to provide a voltage of 1.4V (typ.). This output can be connected directly to either of the comparator inputs as a reference voltage when interfacing with TTL outputs.

ABSOLUTE MAXIMUM RATINGS (Over operating free-air temperature range unless otherwise noted.)

PARAMETER		8T	UNIT
V _{CC}	Supply voltage, positive	7.0	V
V _{EE}	Supply voltage, negative	−7.0	V
V _{DIF}	Differential input voltage	±5.5	V
V _{IN}	Input voltage	−0.5 to +5.5	V
V _{OUT}	Voltage applied to output in HIGH output state	−0.5 to +V _{CC}	V
T _A	Operating free-air temperature range	0 to 70	°C

RECOMMENDED OPERATING CONDITIONS

PARAMETER		8T			UNIT
		Min	Nom	Max	
V _{CC}	Supply voltage, positive	4.75	5.0	5.25	V
V _{EE}	Supply voltage, negative	-4.75	5.0	-5.25	V
V _{IH}	HIGH-level input voltage	2.0			V
V _{IL}	LOW-level input voltage			0.8	V
I _{IK}	Input clamp current			-12	mA
I _{OH}	HIGH-level output current			-800	μA
I _{OL}	LOW-level output current			16	mA
T _A	Operating free-air temperature	0		70	°C

Multivibrator

8T20

DC ELECTRICAL CHARACTERISTICS (Over recommended operating free-air temperature range unless otherwise noted.)

PARAMETER	TEST CONDITIONS ¹	8T20		UNIT
		Min	Max	
V _{IH} Input HIGH voltage	Guaranteed input HIGH threshold voltage	2.0		V
V _{IL} Input LOW voltage	Guaranteed input LOW threshold voltage		0.8	V
V _{IK} Input clamp diode voltage	V _{CC} = MIN, I _{IK} = -12mA		-1.5	V
V _{OH} HIGH-level output voltage	V _{CC} = MIN, I _{OH} = -800μA	2.4		V
V _{OL} LOW-level output voltage	V _{CC} = MIN, I _{OL} = 16mA		0.4	V
I _{IH} HIGH-level input current	V _{CC} = MAX, V _I = 4.5V		40	μA
I _{IL} LOW-level input current	V _{CC} = MAX, V _I = 0.4V PEC, NEC		-2.4	mA
I _{IL} Low level input current	V _{CC} = MAX, V _I = 0.4V mR		-1.6	mA
I _{OS} Short-circuit output current ³	V _{CC} = MAX	-20	-70	mA
I _{CC} Supply current (total)	V _{CC} = 5.25V		55	mA
I _{EE} Supply current (total)	V _{CC} = 5.25V		-20	mA

DIFFERENTIAL INPUTS

V _T Input threshold voltage ⁴		±4		mV
I _B Input bias current ⁵	V _{CC} = +5V, V _{EE} = -5V		125	μA
I _{OS} Input offset current		2		μA
V _{CM} Common mode input volt, range ⁶		-3.2	+4.2	V

NOTES:

- For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions for the applicable type.
- All typical values are at V_{CC} = 5V, T_A = 25°C.
- I_{OS} is tested with V_{OUT} = +0.5V and V_{CC} = V_{CC} MAX + 0.5V. Not more than one output should be shorted at a time and duration of the short circuit should not exceed one second.
- The differential input threshold voltage (V_T) is defined as the maximum DC voltage from the reference level necessary to trigger the one-shot.
- Refer to Figure 5.
- Common mode voltages that are confined within the dynamic range as specified will not cause false triggering of the one-shot.



AC ELECTRICAL CHARACTERISTICS T_A = 25°C, V_{CC} = 5.0V

CHARACTERISTICS	TEST CONDITIONS	LIMITS			UNITS
		Min	Typ	Max	
Output frequency	Fig. 1, f _{in} = 8MHz	16			MHz
Propagation delay	Fig. 2 Fig. 4		30	50	ns
Input to Q, $\bar{Q}$			30	50	ns
Input to A, $\bar{A}$			20	30	ns
MR to Q, $\bar{Q}$					
Reference voltage (V _{REF})	Pin 7 tied to pin 6	0.8	1.4	2.0	V
Output pulse width, fig. 1	Rx = 10K, Cx = open	10		40	ns
Output pulse width, fig. 3	Rx = 10K, Cx = 100pF	600		800	ns

Multivibrator

8T20


AC TEST CIRCUITS AND WAVEFORMS

Figure 1. Minimum Output Pulse Width ($C_{X2} = \text{OPEN}$)Figure 2. Propagation Delay (Input To Q, $\bar{Q}$ Outputs)

Multivibrator


8T20

AC TEST CIRCUITS AND WAVEFORMS (Continued)



TC030105

Figure 3. Propagation Delay (MR To Q, Q̄)




TC030205

Figure 4. Propagation Delay (Input To A, Ā Output)

Multivibrator

8T20

INPUT BIAS CURRENT TEST CIRCUIT



INPUT/OUTPUT WAVEFORMS

