

MSK

M.S.KENNEDY CORP.


**DUAL POSITIVE/NEGATIVE,
3 AMP, LOW DROPOUT
FIXED VOLTAGE REGULATORS****5000
SERIES**

4707 Dey Road Liverpool, N.Y. 13088


(315) 701-6751

FEATURES:

- Dual Low Dropout Voltage
- Internal Short Circuit Current Limit
- Output Voltages Are Internally Set To $\pm 1\%$ Max
- Electrically Isolated Case
- Internal Thermal Overload Protection
- Many Output Voltage Combinations
- Alternate Package and Lead Form Configurations Available

**DESCRIPTION:**

The MSK 5000 Series offers low dropout voltages on both the positive and negative regulators. This, combined with the low θ_{JC} , allows increased output current while providing exceptional device efficiency. Because of the increased efficiency, a small hermetic 5 pin package can be used providing maximum performance while occupying minimal board space. Output voltages are internally trimmed to $\pm 1\%$ maximum resulting in consistent and accurate operation. Additionally, both regulators offer internal short circuit current and thermal limiting, which allows circuit protection and eliminates the need for external components and excessive derating.

EQUIVALENT SCHEMATIC**TYPICAL APPLICATIONS**

- High Efficiency Linear Regulators
- Constant Voltage/Current Regulators
- System Power Supplies
- Switching Power Supply Post Regulators

PIN-OUT INFORMATION

- 1 + Vin
- 2 + Vout
- 3 GND
- 4 -Vin
- 5 -Vout

ABSOLUTE MAXIMUM RATINGS ^⑨

| | | | | |
|--------------|----------------------------------------------------|----------|----------------------------------|-----------------|
| $\pm V_{IN}$ | Input Voltage (WRT V_{OUT}) $\pm 30V$ | T_{ST} | Storage Temperature Range | -65°C to +150°C |
| P_D | Power Dissipation Internally Limited | T_{LD} | Lead Temperature Range | 300°C |
| I_{OUT} | Output Current $\pm 3A$ | | (10 Seconds) | |
| T_J | Junction Temperature +150°C | T_C | Case Operating Temperature | |
| | | | MSK 5000-5009 | -40°C to +85°C |
| | | | MSK 5000B/E-5009B/E | -55°C to +125°C |

ELECTRICAL SPECIFICATIONS

| Parameter | Test Conditions ^③ | Group A Subgroup | MSK 5000B/E SERIES | | | MSK 5000 SERIES | | | Units |
|------------------------------------------|---------------------------------------------------------------------|------------------|--------------------|------|------|-----------------|------|------|-------|
| | | | Min. | Typ. | Max. | Min. | Typ. | Max. | |
| POSITIVE OUTPUT REGULATORS: | | | | | | | | | |
| Output Voltage Tolerance | $I_{OUT} = 0A$; $V_{IN} = V_{OUT} + 3V$ | 1 | - | 0.1 | 1.0 | - | 0.1 | 2.0 | % |
| | | 2,3 | - | 0.1 | 2.0 | - | - | - | % |
| Dropout Voltage ^② | $0A \leq I_{OUT} \leq 3A$; $\Delta V_{OUT} = 50mV$ | 1 | - | 1.3 | 1.5 | - | 1.3 | 1.6 | V |
| Load Regulation | $100mA \leq I_{OUT} \leq 3A$ $V_{IN} = V_{OUT} + 3V$ | 1 | - | 0.2 | 1 | - | 0.2 | 2 | % |
| | | 2,3 | - | 0.3 | 2 | - | - | - | % |
| Line Regulation | $I_{OUT} = 0A$ $(V_{OUT} + 3V) \leq V_{IN} \leq (V_{OUT} + 15V)$ | 1 | - | 0.1 | 0.5 | - | 0.1 | 0.6 | % |
| | | 2,3 | - | 0.2 | .75 | - | - | - | % |
| Quiescent Current | $V_{IN} = V_{OUT} + 3V$; $I_{OUT} = 0A$ | 1,2,3 | - | 10 | 15 | - | 10 | 15 | mA |
| Short Circuit Current ^② | $V_{IN} = V_{OUT} + 5V$ | - | 3.2 | 4 | - | 3.0 | 4 | - | A |
| Ripple Rejection ^② | $I_{OUT} = 3A$; $C_{OUT} = 25\mu F$; $f = 120Hz$ | - | 60 | 75 | - | 60 | 75 | - | dB |
| Thermal Resistance ^② | JUNCTION TO CASE @ $T_C = 125^\circ C$ | - | - | 4.3 | 4.5 | - | 4.3 | 4.6 | °C/W |
| NEGATIVE OUTPUT REGULATORS: ^⑧ | | | | | | | | | |
| Output Voltage Tolerance | $I_{OUT} = 0A$; $V_{IN} = V_{OUT} + 3V$ | 1 | - | 0.1 | 1.0 | - | 0.1 | 2.0 | % |
| | | 2,3 | - | 0.1 | 2.0 | - | - | - | % |
| Dropout Voltage ^② | $0A \leq I_{OUT} \leq 3A$; $\Delta V_{OUT} = 50mV$ | 1 | - | 0.8 | 1.2 | - | 0.8 | 1.3 | V |
| Load Regulation | $V_{IN} = V_{OUT} + 3V$ $100mA \leq I_{OUT} \leq 3A$ | 1 | - | 0.2 | 1 | - | 0.2 | 2 | % |
| | | 2,3 | - | 0.3 | 2 | - | - | - | % |
| Line Regulation | $I_{OUT} = 0A$ $(V_{OUT} + 3V) \leq V_{IN} \leq (V_{OUT} + 15V)$ | 1 | - | .1 | .5 | - | .1 | .6 | % |
| | | 2,3 | - | .2 | .75 | - | - | - | % |
| Quiescent Current | $V_{IN} = V_{OUT} + 3V$; $I_{OUT} = 0A$ | 1,2,3 | - | 4.5 | 10 | - | 4.5 | 10 | mA |
| Short Circuit Current ^② | $V_{IN} = V_{OUT} + 5V$ | - | 3.0 | 3.5 | - | 3.0 | 3.5 | - | A |
| Ripple Rejection ^② | $I_{OUT} = 3A$; $C_{OUT} = 25\mu F$; $f = 120Hz$ | - | 60 | 75 | - | 60 | 75 | - | dB |
| Thermal Resistance ^② | JUNCTION TO CASE @ $T_C = 125^\circ C$ | - | - | 4.5 | 4.7 | - | 4.5 | 4.8 | °C/W |

| PART ^⑦ NUMBER | OUTPUT VOLTAGES | |
|--------------------------|-----------------|----------|
| | POSITIVE | NEGATIVE |
| MSK5000 | + 3.3V | -5.2V |
| MSK5001 | + 5.0V | -5.0V |
| MSK5002 | + 5.0V | -5.2V |
| MSK5003 | + 12.0V | -5.0V |
| MSK5004 | + 12.0V | -12.0V |
| MSK5005 | + 15.0V | -15.0V |
| MSK5006 | + 15.0V | -5.0V |
| MSK5007 | + 5.0V | -12.0V |
| MSK5008 | + 5.0V | -15.0V |
| MSK5009 | + 10.0V | -10.0V |

NOTES:

- ① Outputs are decoupled to ground using 33 μF minimum low ESR capacitors unless otherwise specified.
- ② Guaranteed by design but not tested. Typical parameters are representative of actual device performance but are for reference only.
- ③ All output parameters are tested using a low duty cycle pulse to maintain $T_J = T_C$.
- ④ Industrial grade and "E" suffix devices shall be tested to subgroup 1 unless otherwise specified.
- ⑤ Military grade devices ("H" suffix) shall be 100% tested to subgroups 1,2 and 3.
- ⑥ Subgroup 1 $T_A = T_C = +25^\circ C$
Subgroup 2 $T_A = T_C = +125^\circ C$
Subgroup 3 $T_A = T_C = -55^\circ C$
- ⑦ Please consult the factory if alternate output voltages are required.
- ⑧ Input voltage ($V_{IN} = V_{OUT} +$ a specified voltage) is implied to be more negative than V_{OUT} .
- ⑨ Continuous operation at or above absolute maximum ratings may adversely effect the device performance and/or life cycle.

BYPASS CAPACITORS

For most applications a 33uF minimum, low ESR (0.5-2 ohm) tantalum capacitor should be attached as close to the regulator's output as possible. This will effectively lower the regulator's output impedance, increase transient response and eliminate any oscillations that are normally associated with low dropout regulators. Additional bypass capacitors can be used at the remote load locations to further improve regulation. These can be either of the tantalum or the electrolytic variety. Unless the regulator is located very close to the power supply filter capacitor(s), a 4.7uF minimum low ESR (0.5-2 ohm) tantalum capacitor should also be added to the regulator's input. An electrolytic may also be substituted if desired. When substituting electrolytic in place of tantalum capacitors, a good rule of thumb to follow is to increase the size of the electrolytic by a factor of 10 over the tantalum value.

LOAD REGULATION

For best results the ground pin should be connected directly to the load as shown below, this effectively reduces the ground loop effect and eliminates excessive voltage drop in the sense leg. It is also important to keep the output connection between the regulator and the load as short as possible since this directly affects the load regulation. For example, if 20 gauge wire were used which has a resistance of about .008 ohms per foot, this would result in a drop of 8mV/ft at 1Amp of load current. It is also important to follow the capacitor selection guidelines to achieve best performance. Refer to Figure 2 for connection diagram.

MSK 5002 TYPICAL APPLICATION:

Low Dropout Positive and Negative Power Supply




FIGURE 1

Avoiding Ground Loops




FIGURE 2

OVERLOAD SHUTDOWN

The regulators feature both power and thermal overload protection. When the maximum power dissipation is not exceeded, the regulators will current limit slightly above their 3 amp rating. As the $V_{in}-V_{out}$ voltage increases, however, shutdown occurs in relation to the maximum power dissipation curve. If the device heats enough to exceed its rated die junction temperature due to excessive ambient temperature, improper heat sinking etc., the regulators also shutdown until an appropriate junction temperature is maintained. It should also be noted that in the case of an extreme overload, such as a sustained direct short, the device may not be able to recover. In these instances, the device must be shut off and power reapplied to eliminate the shutdown condition.

HEAT SINKING

To determine if a heat sink is required for your application and if so, what type, refer to the thermal model and governing equation below.

Governing Equation: $T_j = P_d \times (R_{\theta jc} + R_{\theta cs} + R_{\theta sa}) + T_a$

WHERE

- T_j = Junction Temperature
- P_d = Total Power Dissipation
- $R_{\theta jc}$ = Junction to Case Thermal Resistance
- $R_{\theta cs}$ = Case to Heat Sink Thermal Resistance
- $R_{\theta sa}$ = Heat Sink to Ambient Thermal Resistance
- T_c = Case Temperature
- T_a = Ambient Temperature
- T_s = Heat Sink Temperature

EXAMPLE:

This example demonstrates an analysis where each regulator is at one-half of its maximum rated power dissipation, which occurs when the output currents are at 1.5 amps each.

Conditions for MSK 5002:

$$V_{in} = \pm 7.0V; I_{out} = \pm 1.5A$$

- 1.) Assume 45° heat spreading model.
- 2.) Find positive regulator power dissipation:

$$\begin{aligned} P_d &= (V_{in} - V_{out})(I_{out}) \\ P_d &= (7-5)(1.5) \\ &= 3.0W \end{aligned}$$

- 3.) For conservative design, set $T_j = +125^\circ C$ Max.
- 4.) For this example, worst case $T_a = +90^\circ C$.
- 5.) $R_{\theta jc} = 4.5^\circ C/W$ from the Electrical Specification Table.
- 6.) $R_{\theta cs} = 0.15^\circ C/W$ for most thermal greases.
- 7.) Rearrange governing equation to solve for $R_{\theta sa}$:


$$\begin{aligned} R_{\theta sa} &= ((T_j - T_a)/P_d) - (R_{\theta jc}) - (R_{\theta cs}) \\ &= (125^\circ C - 90^\circ C)/3.0W - 4.5^\circ C/W - 0.15^\circ C/W \\ &= 7.0^\circ C/W \end{aligned}$$

The same exercise must be performed for the negative regulator. In this case the result is 7.0°C/W. Therefore, a heat sink with a thermal resistance of no more than 7.0°C/W must be used in this application to maintain both regulator circuit junction temperatures under 125°C.


TYPICAL PERFORMANCE CURVES

POSITIVE REGULATORS


DROPOUT VOLTAGE vs. OUTPUT CURRENT




INTERNAL CURRENT LIMIT vs. VIN-VOUT



RIPPLE REJECTION vs. FREQUENCY




POWER DISSIPATION vs. TEMPERATURE




NEGATIVE REGULATORS


DROPOUT VOLTAGE vs. OUTPUT CURRENT




INTERNAL CURRENT LIMIT vs. VIN-VOUT





RIPPLE REJECTION vs. FREQUENCY



POWER DISSIPATION vs. TEMPERATURE




MECHANICAL SPECIFICATIONS



NOTE: ESD Triangle indicates Pin 1.
 ALL DIMENSIONS ARE ± 0.010 INCHES UNLESS OTHERWISE LABELED

ORDERING INFORMATION



THE ABOVE EXAMPLE IS A + 3.3V, -5.2V MILITARY REGULATOR USING THE TOP TAB PACKAGE WITH LEADS BENT UP.

M.S. Kennedy Corp.
 4707 Dey Road, Liverpool, New York 13088
 Phone (315) 701-6751
 FAX (315) 701-6752
 www.mskennedy.com

The information contained herein is believed to be accurate at the time of printing. MSK reserves the right to make changes to its products or specifications without notice, however, and assumes no liability for the use of its products. Please visit our website for the most recent revision of this datasheet.