

DATA SHEET

FI1216MK2

Desktop video tuner system CCIR B/G

Preliminary specification

1997 Mar 13

Supersedes data of 1996 Feb 16


File under Display Components, DC03

Desktop video tuner system CCIR B/G

FI1216MK2

FEATURES

- System CCIR B/G
- True 5 V device (low power dissipation)
- Full frequency range from channel 2 (48.25 MHz) to channel 69 (855.25 MHz)
- PLL controlled tuning
- True-synchronous vision IF demodulator (PLL)
- Demodulated video output, AF sound output, second sound IF output
- I²C-bus control of tuning, address selection, AFC status information
- Complies with European regulations on radiation, signal handling and immunity ("CENELEC 55020, 55013" and "Amtsblatt 15/92")
- Small horizontally mounted metal housing.



The analog AFC voltage is fed to the 5-level A/D converter in the PLL tuning IC, so that the AFC status can be read via the I²C-bus.

ORDERING INFORMATION

| TYPE | DESCRIPTION | CATALOGUE NUMBERS |
|------------------|----------------|-------------------|
| FI1216MK2/HM/PH | standard phono | 3139 147 13291 |
| FI1216MK2/HM/IEC | IEC | 3139 147 13301 |

MARKING

The following items of information are printed on a sticker that is on the top cover of the tuner:

- Type number
- Code number
- Origin letter of factory
- Change code
- Year and week code.

INTERMEDIATE FREQUENCIES

| SYSTEM | FREQUENCY ⁽¹⁾ (MHz) |
|-----------------|-----------------------------------|
| | PAL B/G |
| Picture carrier | 38.90 |
| Colour | 34.47 |
| Sound 1 | 33.40 |
| Sound 2 | 33.16 |
| NICAM | 33.05 |

Note

1. The oscillator frequency is above the input signal frequency.

CHANNEL COVERAGE

| BAND | CHANNELS |
|-----------|----------------------|
| Low band | 48.25 to 170.00 MHz |
| Mid band | 170.00 to 450.00 MHz |
| High band | 450.00 to 855.25 MHz |

Desktop video tuner system CCIR B/G

FI1216MK2


BLOCK DIAGRAM

Fig 1 Electrical block diagram.

**Desktop video tuner
system CCIR B/G****FI1216MK2****PINNING**

| SYMBOL | PIN | DESCRIPTION |
|---------------------------------|-----------------------|--|
| V _T | 11 | tuning voltage (monitor) |
| V _s | 12 | supply voltage tuner section +5 V |
| SCL | 13 | I ² C-bus serial clock |
| SDA | 14 | I ² C-bus serial data |
| AS | 15 | I ² C-bus address select |
| n.c. | 21 | not connected |
| 2 nd IF sound output | 22 | second IF sound output |
| CVBS | 23 | Composite Video Baseband Signal output |
| V _{IF} | 24 | supply voltage IF section +5 V |
| AF sound output | 25 | AF sound output |
| — | TH1, TH2, TH3 and TH4 | mounting tags (ground) |

Desktop video tuner system CCIR B/G

FI1216MK2

LIMITING VALUES**Limiting values under operational conditions**

The tuner can be guaranteed to function properly under the following conditions.

| SYMBOL | PARAMETER | PIN | MIN. | TYP. | MAX. | UNIT |
|-------------------------|--|-----|------|------|-------|------|
| V_S | supply voltage | 12 | 4.75 | 5.00 | 5.25 | V |
| $V_{S(\text{ripple})}$ | peak-to-peak ripple voltage susceptibility (at 5 V $\pm 5\%$); note 1 20 Hz to 100 kHz >100 kHz to 500 kHz | | — | — | 20 | mV |
| I_S | supply current | | — | — | 120 | mA |
| V_{SCL} | SCL bus input voltage | 13 | -0.3 | — | +5.25 | V |
| V_{SDA} | SDA bus input voltage | 14 | -0.3 | — | +5.25 | V |
| I_{SDA} | SDA bus current (open collector) | | -1 | — | +5 | mA |
| V_{AS} | address select voltage; note 2 | 15 | — | — | +5.25 | V |
| Z_{IF} | 2 nd IF sound output load impedance: DC AC | 22 | 0.5 | — | — | kΩ |
| Z_{CVBS} | Composite Video Baseband Signal load impedance: DC AC | 23 | — | 75 | — | Ω |
| t_L | load time constant | | — | 75 | — | Ω |
| t_L | load time constant | | — | — | 100 | ns |
| V_{IF} | IF supply voltage | 24 | 4.75 | 5.0 | 5.25 | V |
| $V_{IF(\text{ripple})}$ | peak-to-peak ripple voltage susceptibility (at 5 V $\pm 5\%$); note 1 20 Hz to 100 kHz >100 kHz to 500 kHz | | — | — | 20 | mV |
| I_{IF} | IF supply current | | — | — | 100 | mA |
| Z_{AF} | AF sound output load impedance: DC AC | | 25 | 1.0 | — | kΩ |
| | | | | 0.6 | — | kΩ |

Notes

1. Sinusoidal ripple voltage superimposed on the 5 V supply voltage in the frequency range of 20 Hz to 500 kHz.
Criteria for TV interference >57 dB.
2. For detailed information about the address decoding, refer to Chapter "Application information".

**Desktop video tuner
system CCIR B/G**
FI1216MK2**Environmental conditions**

| SYMBOL | PARAMETER | CONDITIONS | MIN. | TYP. | MAX. | UNIT |
|-----------------------------------|---------------------|-------------|------|------|------|------------------|
| Non-operational conditions | | | | | | |
| T _{amb} | ambient temperature | | -25 | - | +85 | °C |
| RH | relative humidity | | - | - | 100 | % |
| g _B | bump acceleration | 25 g | - | - | 245 | m/s ² |
| g _S | shock acceleration | 50 g | - | - | 490 | m/s ² |
| | vibration amplitude | 10 to 55 Hz | - | 0.35 | - | mm |
| Operational conditions | | | | | | |
| T _{amb} | ambient temperature | | -10 | - | +60 | °C |
| RH | relative humidity | | - | - | 95 | % |

OVERALL PERFORMANCE**Conditional data**

Unless otherwise specified, all electrical values for Chapter "Overall performance" apply at the following conditions.

| SYMBOL | PARAMETER | VALUE | UNIT |
|--------------------|---------------------------------------|----------|--------|
| T _{amb} | ambient temperature | 25 ±5 | °C |
| RH | relative humidity | 60 ±15 | % |
| V _S | supply voltage (tuner and IF section) | 5 ±0.125 | V |
| Z _{CVBS} | video output load impedance (DC) | >75 | Ω |
| Z _{IF} | IF sound output load impedance (DC) | >500 | Ω |
| t _{pr} | pre-heating time (+5 V at pin 24) | 10 | minute |
| Z _{S(AE)} | aerial source impedance (unbalanced) | 75 | Ω |

Desktop video tuner system CCIR B/G

FI1216MK2

TUNER SECTION**Tuner characteristics**

For detailed information about the PLL programming, refer to Chapter "Application information".


The desktop video tuner is guaranteed to function properly within the specified operational conditions, but a certain deterioration of performance parameters may occur at the limits of the operational conditions.

Test equipment

| EQUIPMENT | PARAMETER | VALUE | UNIT |
|-------------------|---|-----------|----------|
| DC voltmeter | input impedance | >1 | MΩ |
| Oscilloscope | input impedance: resistance capacitance | >1 <15 | MΩ pF |
| Spectrum analyzer | input impedance | 50 | Ω |
| FET probe | input impedance: resistance capacitance | 1 3.5 | MΩ pF |
| | output impedance | 50 | Ω |
| | voltage gain | 0 | dB |

Desktop video tuner system CCIR B/G

FI1216MK2



(1) BU4 loaded with 75 Ω.

(2) 50 μs de-emphasis.

SA = spectrum analyzer.

P = FET probe.

DA = distortion analyzer.

Fig.2 Typical test set up.

Desktop video tuner system CCIR B/G

FI1216MK2

Definitions of test signals (see Fig.2)

| TEST SIGNAL | FREQ. (MHz) | AMPLITUDE | MODULATION | |
|--|----------------|---------------------------|---|--|
| | | | VIDEO | AUDIO |
| A0: unmodulated vision carrier | 480.25 | 60 dB μ V | | |
| A1: CCIR B/G standard signal with video modulation | 480.25 | 60 dB μ V (top sync) | 100% (rest carrier 10%) 2T pulse and bar | |
| B1: unmodulated sound carrier B/G system | 485.75 | -13 dB w.r.t. A0 to A1 | | |
| B2: FM modulated sound carrier B/G system | 485.75 | -13 dB w.r.t. A0 to A1 | | 1 kHz; modulation frequency deviation ± 27 kHz; 50 μ s pre-emphasis |
| B3: unmodulated sound carrier B/G system | 478.75 | -13 dB w.r.t. A0 to A1 | | |

Aerial input characteristics

| SYMBOL | PARAMETER | CONDITIONS | MIN. | MAX. | UNIT |
|-----------|--|--|------|------|------------|
| VSWR | reflection coefficient | referred to 75 Ω impedance (worst case on or between picture and sound carrier at maximum gain) | — | 5 | |
| V_{PSM} | surge protection voltage | | 5 | — | kV |
| V_{ant} | antenna connection disturbance voltage | <1.75 GHz | — | 46 | dB μ V |

Desktop video tuner system CCIR B/G

FI1216MK2

General characteristics

| SYMBOL | PARAMETER | CONDITIONS | MIN. | TYP. | MAX. | UNIT |
|---------------|--|--|---------------------------|-------------------------|----------------------------|--|
| f_b | frequency range: low band mid band high band | | 48.25 175.25 455.25 | — — — | 168.25 447.25 855.25 | MHz MHz MHz |
| Δf_b | margin: for low band for mid/high band | | 1.5 3 | — — | — — | MHz MHz |
| α_i | image rejection (nominal gain to 10 dB gain reduction): low band mid band mid band high band | <300 MHz 66 >300 MHz 60 50 | 70 — — — — | — — — — — | — — — — — | dB dB dB dB |
| α_{IF} | IF rejection (picture) | | 60 | — | — | dB |
| Z_{IF} | ½ IF susceptibility: E2 to E12 E21 to E69 | | 75 60 | — — | — — | $\text{dB}\mu\text{V}$ $\text{dB}\mu\text{V}$ |
| α_s | sound-chrominance moiré rejection: off-air UHF | up to 40 dB gain control up to 30 dB minimum gain control | 56 56 | — — | — — | dB dB |
| m_x | cross modulation: in-channel in-band low band ($n \pm 2$) mid band ($n \pm 3$) high band ($n \pm 5$) out of band | | 70 78 78 84 — | — — — — 100 | — — — — — | $\text{dB}\mu\text{V}$ $\text{dB}\mu\text{V}$ $\text{dB}\mu\text{V}$ $\text{dB}\mu\text{V}$ $\text{dB}\mu\text{V}$ |
| | breakthrough susceptibility: E2 to E12; E21 to E69 | | 60 | — | — | $\text{dB}\mu\text{V}$ |
| V_{osc} | oscillator voltage at all pins | | — | — | 70 | $\text{dB}\mu\text{V}$ |
| t_{li} | oscillators lock-in time | charge pump set logic HIGH | — | — | 150 | ms |
| α_{vs} | the video signal-to-sound interference ratio with the tuner exposed to sound signals in the audio frequency range 100 Hz to 10 kHz and sound pressure levels up to 105 dB (20 μPa) | | 40 | — | — | dB |
| V_{ESD} | electrostatic discharge (ESD) on all pins | note 1 | 2 | — | — | kV |

Note

1. All the pins of the desktop video tuner are protected against electrostatic discharge (ESD) up to 2 kV. The product is classified in category B ("MIL-STD-883C").

Desktop video tuner system CCIR B/G

FI1216MK2

Video and audio characteristics (see Fig.2)

| PARAMETER | TEST SIGNAL | TEST POINT | MIN. | TYP. | MAX. | UNIT |
|---|--|------------|------|------|------|------------|
| CVBS characteristics: | | | | | | |
| video amplitude signal at pin 23 | A1 (peak-to-peak value) | BU4 | 0.7 | — | 1.1 | V |
| DC level sync pulse at pin 23 | A1 | BU4 | — | 0.35 | — | V |
| Video amplitude drop with respect to modulation 0.1 MHz at $T_{amb} = 45^{\circ}\text{C}$: | | | | | | |
| at 1 MHz | A1 | BU4 | -1.0 | — | +1.0 | dB |
| at 2 MHz | A1 | BU4 | -1.5 | — | +1.5 | dB |
| at 3 MHz | A1 | BU4 | -2.5 | — | +1.5 | dB |
| at 4 MHz | A1 | BU4 | -3.0 | — | +2.0 | dB |
| at 4.43 MHz | A1 | BU4 | -4.0 | — | +2.0 | dB |
| Sound carrier rejection | A1 (1 MHz) + B1 | BU4 | 40 | — | — | dB |
| Residual 40.4 MHz signal in video channel: level of 1.5 MHz | A1 + B3 | BU4 | — | — | 68 | dB μ V |
| Residual 77.8 MHz signal in video channel | A1 | BU4 | — | — | 80 | dB μ V |
| Second IF sound output level at level of 5.5 MHz | A1 + B1 | BU5 | 84 | — | — | dB μ V |
| Test on 2T pulse at $T_{amb} = 45^{\circ}\text{C}$: | | | | | | |
| 2T pulse/bar response | A1 | BU4 | -2.5 | — | +2.5 | % |
| 2T pulse response | A1 | BU4 | — | — | +3.0 | % |
| CVBS S/N (unweighted) | A1 + B1 | BU4 | 41 | — | — | dB |
| Gain limited sensitivity at 1 dB reduction of video output | A1 | BU4 | — | — | 30 | dB μ V |
| Audio characteristics: | | | | | | |
| AF output level measured via LP 20 kHz filter, RMS detector, 50 μ s de-emphasis | A1 + B2 | BU6 | 0.25 | 0.35 | 0.50 | V |
| THD (Total Harmonic Distortion) measured via LP 20 kHz filter, RMS detector, 50 μ s de-emphasis | A1 + B2 | BU6 | — | — | 0.5 | % |
| S/N measured via CCIR filter, peak CCIR detector, 50 μ s de-emphasis | A1 (6 kHz sine wave, black-to-white) + B1 | BU6 | 41 | — | — | dB |
| AF 3 dB response measured via LP 20 kHz filter, RMS detector, de-emphasis off | A1 (black) + B1 | BU6 | 16 | — | — | kHz |
| AM suppression ratio | A1 + B2 | BU6 | 40 | — | — | dB |

Digital AFC status

| PARAMETER | CONDITIONS | FREQUENCY (kHz) | DIGITAL READ-OUT |
|--|---|--------------------|---------------------|
| ADC word at I ² C-bus during read operation | input voltage at pin 10: 0.0 to 0.15V _S | -125 | 00 |
| | input voltage at pin 10: 0.15 to 0.30V _S | -62.5 | 01 |
| | input voltage at pin 10: 0.30 to 0.45V _S | 0 | 02 |
| | input voltage at pin 10: 0.45 to 0.60V _S | +62.5 | 03 |
| | input voltage at pin 10: 0.60 to 1.00V _S | +125 | 04 |

Desktop video tuner system CCIR B/G

FI1216MK2

APPLICATION INFORMATION

A detailed description of the I²C-bus specification, with applications, is given in brochure "The I²C-bus and how to use it". This brochure may be ordered using the code number 9398 393 40011.

WRITE mode

| BYTE | BITS | | | | | | | | |
|----------------------------|----------|-----|-----|-----|-----|-----|-----|----------|------------------|
| | 7 MSB | 6 | 5 | 4 | 3 | 2 | 1 | 0 LSB | A ⁽¹⁾ |
| Address byte | 1 | 1 | 0 | 0 | 0 | MA1 | MA0 | 0 | A |
| Program divider byte 1 | 0 | n14 | n13 | n12 | n11 | n10 | n9 | n8 | A |
| Program divider byte 2 | n7 | n6 | n5 | n4 | n3 | n2 | n1 | n0 | A |
| Control information byte 1 | 1 | CP | T2 | T1 | T0 | RSA | RSB | OS | A |
| Control information byte 2 | P7 | P6 | P5 | P4 | P3 | P2 | P1 | P0 | A |

Note

1. A = Acknowledge.

ADDRESS SELECTION

V_S = +5 V (PLL supply voltage).

| MA1 | MA0 | ADDRESS | VOLTAGE AT PIN 15 |
|-----|-----|---------|--|
| 0 | 0 | C0 | 0.0V _S to 0.1V _S |
| 0 | 1 | C2 | 0.2V _S to 0.3V _S |
| 1 | 0 | C4 | 0.4V _S to 0.6V _S |
| 1 | 1 | C6 | 0.9V _S to 1.0V _S |

PROGRAMMABLE DIVIDER SETTINGS (BYTES 1 AND 2)

Divider ratio:

$$N = 16 \times \{f_{RF(pc)} + f_{IF(pc)}\}, \text{ where (pc) is picture carrier and } f_{RF} \text{ and } f_{IF} \text{ are expressed in MHz}$$

$$f_{osc} = N/16 \text{ (MHz).}$$

$$N = (8192 \times n13) + (4096 \times n12) + (2048 \times n11) + (1024 \times n10) + (512 \times n9) + (256 \times n8) + (128 \times n7) + (64 \times n6) + (32 \times n5) + (16 \times n4) + (8 \times n3) + (4 \times n2) + (2 \times n1) + n0$$

CONTROL BYTE

Charge pump settings:

CP = 1, for fast tuning

CP = 0, for moderate speed tuning with slightly better residual oscillator FM.

Test mode settings:

T2 = T1 = 0; T0 = 1, for normal operation.

PLL disabling:

OS = 0, for normal operation

OS = 1, for switching the charge pump to the high impedance state.

Desktop video tuner system CCIR B/G

FI1216MK2

Ratio select bits

| RSA | RSB | STEP SIZE |
|-----|-----|--------------------------------------|
| X | 0 | 50 kHz |
| 0 | 1 | 31.25 kHz (for slow picture search) |
| 1 | 1 | 62.5 kHz (for normal picture search) |

PORTS BYTE

Band switching

| BAND | BIT ⁽¹⁾ | | | | | | | |
|-----------|--------------------|----|----|-------------------|----|----|----|----|
| | P0 | P1 | P2 | P3 ⁽²⁾ | P4 | P5 | P6 | P7 |
| Low band | 0 | 0 | 0 | X | 0 | 1 | 0 | 1 |
| Mid band | 0 | 0 | 0 | X | 1 | 0 | 0 | 1 |
| High band | 0 | 0 | 0 | X | 1 | 1 | 0 | 0 |

Notes

1. X = don't care; P0 to P7 are output ports on the PLL device.
2. P3 is a system switch output for customer applications.

TELEGRAM EXAMPLES (WRITE MODE)

Start - Adb - Ack - Db1 - Ack - Db2 - Ack - Cb - Ack - Pb - Ack - Stop.

Start - Adb - Ack - Cb - Ack - Pb - Ack - Db1 - Ack - Db2 - Ack - Stop.

Start - Adb - Ack - Db1 - Ack - Db2 - Ack - Cb - Ack - Stop.

Start - Adb - Ack - Db1 - Ack - Db2 - Ack - Stop.

Where:

Start = start condition

Adb = address byte

Ack = acknowledge

Db1 = divider byte 1

Db2 = divider byte 2

Cb = control byte

Pb = ports byte

Stop = stop condition.

Remark: for channel selection involving band switching, and to ensure smooth tuning to the desired channel without causing unnecessary charge pump action, it is recommended to consider the difference between wanted channel frequency (f_w) and the current channel frequency (f_c):

- If $f_w > f_c$, use telegram as:

Start - Adb - Ack - Db1 - Ack - Db2 - Ack - Cb - Ack - Pb - Ack - Stop.

- If $f_w < f_c$, use telegram as:

Start - Adb - Ack - Cb - Ack - Pb - Ack - Db1 - Ack - Db2 - Ack - Stop.

Unnecessary charge pump action will result in very low tuning voltage ($V_T \approx 0$ V) which may drive the oscillator to extreme conditions.

Desktop video tuner system CCIR B/G

FI1216MK2

READ mode

The in-lock can be read by setting the R/W bit to 1.

| BYTE | BITS | | | | | | | | |
|--------------|--------------------|-------------------|-------------------|-------------------|-------------------|-------------------|-------------------|-------------------|------------------|
| | 7 MSB | 6 | 5 | 4 | 3 | 2 | 1 | 0 LSB | A ⁽⁵⁾ |
| Address byte | 1 | 1 | 0 | 0 | 0 | MA1 | MA0 | 1 | A |
| Status byte | POR ⁽¹⁾ | FL ⁽²⁾ | I2 ⁽³⁾ | I1 ⁽³⁾ | I0 ⁽³⁾ | A2 ⁽⁴⁾ | A1 ⁽⁴⁾ | A0 ⁽⁴⁾ | A |

Notes

1. POR = Power On Reset. POR is internally set to 1 in case V_S drops below 3 V. The POR bit is reset when an end of data is detected by the PLL IC.
2. FL = In-lock flag; FL = 1: loop is phase-locked. The loop must be phase-locked during at least 8 periods of the internal 7.8125 kHz reference frequency before the FL flag is internally set to 1.
3. I2, I1 and I0 = digital information for I/O ports P2, P1 and P0 respectively.
4. A2, A1 and A0 = built-in 5-level A/D converter on I/O port P6. AFC information to the controller of the IF section is available on pin 10 (see Table "Digital AFC status").
5. A = Acknowledge.

TELEGRAM EXAMPLES (READ MODE)

Start - Adb - Ack - STB - Ack - STB - - Stop (no Ack from processor = End-of-data).

Start - Adb - Ack - STB - - Stop (no Ack from processor = End-of-data).

Where:

STB = Status byte.

Video buffer

A video buffer is built into the video module to enable the unit to drive a 75Ω load directly. In case it is required to use the FI1216MK2 as a replacement for the FI1216 in the same videocard, it is necessary to replace the 75Ω series resistor in the video card by a 0Ω series resistor. At the same time the $22 \text{ k}\Omega$ series resistor in the tuning supply must be removed.

I²C-bus load

The FI1216MK2 contains a series resistor ($R = 100 \Omega$) in the SCL and SDA lines. Both lines also have a capacitive load of typical 56 pF (see Fig.3).





Fig.3 I²C-bus load.

Desktop video tuner system CCIR B/G

FI1216MK2

MECHANICAL DATA



Desktop video tuner system CCIR B/G

FI1216MK2

Aerial connections

Standard-phono socket female $75\ \Omega$ or IEC (female).

Solderability

The solderability of pins and mounting tags when tested initially and after 16 hours steam ageing in accordance with "IEC 68-2-20", test Ta, method 1 (solder bath $235\ ^\circ\text{C}$ for 2 s), results in a wetted area of 95%. No de-wetting will occur when soldered at $260\ ^\circ\text{C}$ for 5 s.

Resistance to soldering heat

The product will not be damaged when tested in accordance with "IEC 68-2-20", test Tb, method 1A (solder bath $260\ ^\circ\text{C}$ for 10 ± 1 s).

Mass

Approximately 50 g.


Robustness of pins

The pins will not be damaged when tested in accordance with "IEC 68-2-21":

- Test Ua1, tensile of 10 N in axial direction
- Test Ua2, thrust of 4 N in axial direction.

Punching pattern of chassis PCB

Field rejects are often related to broken tag joints. Therefore, the following punching pattern is recommended (see Fig.5).



Dimensions in mm.

Fig.5 Punching pattern seen from solder side.

Desktop video tuner system CCIR B/G

FI1216MK2

TV CHANNEL FREQUENCIES (MHz)**CCIR cable**

Vision IF = 38.90 MHz; sound IF = 33.40 MHz.

| CHANNEL | FREQ. RANGE | PICTURE CARRIER FREQUENCY | SOUND CARRIER FREQUENCY |
|---------|----------------|---------------------------------|-------------------------------|
| E2 | 47-54 | 48.25 | 53.75 |
| E3 | 54-61 | 55.25 | 60.75 |
| E4 | 61-68 | 62.25 | 67.75 |
| S01 | 68-75 | 69.25 | 74.75 |
| S02 | 75-82 | 76.25 | 81.75 |
| S03 | 82-89 | 83.25 | 88.75 |
| S1 | 104-111 | 105.25 | 110.75 |
| S2 | 111-118 | 112.25 | 117.75 |
| S3 | 118-125 | 119.25 | 124.75 |
| S4 | 125-132 | 126.25 | 131.75 |
| S5 | 132-139 | 133.25 | 138.75 |
| S6 | 139-146 | 140.25 | 145.75 |
| S7 | 146-153 | 147.25 | 152.75 |
| S8 | 153-160 | 154.25 | 159.75 |
| S9 | 160-167 | 161.25 | 166.75 |
| S10 | 167-174 | 168.25 | 173.75 |
| E5 | 174-181 | 175.25 | 180.75 |
| E6 | 181-188 | 182.25 | 187.75 |
| E7 | 188-195 | 189.25 | 194.75 |
| E8 | 195-202 | 196.25 | 201.75 |
| E9 | 202-209 | 203.25 | 208.75 |
| E10 | 209-216 | 210.25 | 215.75 |
| E11 | 216-223 | 217.25 | 222.75 |
| E12 | 223-230 | 224.25 | 229.75 |
| S11 | 230-237 | 231.25 | 236.75 |
| S12 | 237-244 | 238.25 | 243.75 |
| S13 | 244-251 | 245.25 | 250.75 |
| S14 | 251-258 | 252.25 | 257.75 |

| CHANNEL | FREQ. RANGE | PICTURE CARRIER FREQUENCY | SOUND CARRIER FREQUENCY |
|---------|----------------|---------------------------------|-------------------------------|
| S15 | 258-265 | 259.25 | 264.75 |
| S16 | 265-272 | 266.25 | 271.75 |
| S17 | 272-279 | 273.25 | 278.75 |
| S18 | 279-286 | 280.25 | 285.75 |
| S19 | 286-293 | 287.25 | 292.75 |
| S20 | 293-300 | 294.25 | 299.75 |
| S21 | 302-310 | 303.25 | 308.75 |
| S22 | 310-318 | 311.25 | 316.75 |
| S23 | 318-326 | 319.25 | 324.75 |
| S24 | 326-334 | 327.25 | 332.75 |
| S25 | 334-342 | 335.25 | 340.75 |
| S26 | 342-350 | 343.25 | 348.75 |
| S27 | 350-358 | 351.25 | 356.75 |
| S28 | 358-366 | 359.25 | 364.75 |
| S29 | 366-374 | 367.25 | 372.75 |
| S30 | 374-382 | 375.25 | 380.75 |
| S31 | 382-390 | 383.25 | 388.75 |
| S32 | 390-398 | 391.25 | 396.75 |
| S33 | 398-406 | 399.25 | 404.75 |
| S34 | 406-414 | 407.25 | 412.75 |
| S35 | 414-422 | 415.25 | 420.75 |
| S36 | 422-430 | 423.25 | 428.75 |
| S37 | 430-438 | 431.25 | 436.75 |
| S38 | 438-446 | 439.25 | 444.75 |
| S39 | 446-454 | 447.25 | 452.75 |
| S40 | 454-462 | 455.25 | 460.75 |
| S41 | 462-470 | 463.25 | 468.75 |

Desktop video tuner system CCIR B/G

FI1216MK2

CCIR B/G

Vision IF = 38.90 MHz; sound IF = 33.40 MHz.

| CHANNEL | FREQ. RANGE | PICTURE CARRIER FREQUENCY | SOUND CARRIER FREQUENCY |
|---------|----------------|---------------------------------|-------------------------------|
| 2 | 47-54 | 48.25 | 53.75 |
| 3 | 54-61 | 55.25 | 60.75 |
| 4 | 61-68 | 62.25 | 67.75 |
| 5 | 174-181 | 175.25 | 180.75 |
| 6 | 181-188 | 182.25 | 187.75 |
| 7 | 188-195 | 189.25 | 194.75 |
| 8 | 195-202 | 196.25 | 201.75 |
| 9 | 202-209 | 203.25 | 208.75 |
| 10 | 209-216 | 210.25 | 215.75 |
| 11 | 216-223 | 217.25 | 222.75 |
| 12 | 223-230 | 224.25 | 229.75 |
| 21 | 470-478 | 471.25 | 476.75 |
| 22 | 478-486 | 479.25 | 484.75 |
| 23 | 486-494 | 487.25 | 492.75 |
| 24 | 494-502 | 495.25 | 500.75 |
| 25 | 502-510 | 503.25 | 508.75 |
| 26 | 510-518 | 511.25 | 516.75 |
| 27 | 518-526 | 519.25 | 524.75 |
| 28 | 526-534 | 527.25 | 532.75 |
| 29 | 534-542 | 535.25 | 540.75 |
| 30 | 542-550 | 543.25 | 548.75 |
| 31 | 550-558 | 551.25 | 556.75 |
| 32 | 558-566 | 559.25 | 564.75 |
| 33 | 566-574 | 567.25 | 572.75 |
| 34 | 574-582 | 575.25 | 580.75 |
| 35 | 582-590 | 583.25 | 588.75 |
| 36 | 590-598 | 591.25 | 596.75 |
| 37 | 598-606 | 599.25 | 604.75 |
| 38 | 606-614 | 607.25 | 612.75 |
| 39 | 614-622 | 615.25 | 620.75 |

| CHANNEL | FREQ. RANGE | PICTURE CARRIER FREQUENCY | SOUND CARRIER FREQUENCY |
|---------|----------------|---------------------------------|-------------------------------|
| 40 | 622-630 | 623.25 | 628.75 |
| 41 | 630-638 | 631.25 | 636.75 |
| 42 | 638-646 | 639.25 | 644.75 |
| 43 | 646-654 | 647.25 | 652.75 |
| 44 | 654-662 | 655.25 | 660.75 |
| 45 | 662-670 | 663.25 | 668.75 |
| 46 | 670-678 | 671.25 | 676.75 |
| 47 | 678-686 | 679.25 | 684.75 |
| 48 | 686-694 | 687.25 | 692.75 |
| 49 | 694-702 | 695.25 | 700.75 |
| 50 | 702-710 | 703.25 | 708.75 |
| 51 | 710-718 | 711.25 | 716.75 |
| 52 | 718-726 | 719.25 | 724.75 |
| 53 | 726-734 | 727.25 | 732.75 |
| 54 | 734-742 | 735.25 | 740.75 |
| 55 | 742-750 | 743.25 | 748.75 |
| 56 | 750-758 | 751.25 | 756.75 |
| 57 | 758-766 | 759.25 | 764.75 |
| 58 | 766-774 | 767.25 | 772.75 |
| 59 | 774-782 | 775.25 | 780.75 |
| 60 | 782-790 | 783.25 | 788.75 |
| 61 | 790-798 | 791.25 | 796.75 |
| 62 | 798-806 | 799.25 | 804.75 |
| 63 | 806-814 | 807.25 | 812.75 |
| 64 | 814-822 | 815.25 | 820.75 |
| 65 | 822-830 | 823.25 | 828.75 |
| 66 | 830-838 | 831.25 | 836.75 |
| 67 | 838-846 | 839.25 | 844.75 |
| 68 | 846-854 | 847.25 | 852.75 |
| 69 | 854-862 | 855.25 | 860.75 |

Desktop video tuner system CCIR B/G

FI1216MK2

Italy

Vision IF = 38.90 MHz; sound IF = 33.40 MHz.


| CHANNEL | PICTURE CARRIER FREQUENCY | SOUND CARRIER FREQUENCY |
|---------|---------------------------|-------------------------|
| A | 53.75 | 59.25 |
| B | 62.25 | 67.75 |
| C | 82.25 | 87.75 |
| D | 175.25 | 180.75 |
| E | 183.75 | 189.25 |
| F | 197.25 | 192.75 |
| G | 201.25 | 206.75 |
| H | 210.25 | 215.75 |
| H1 | 217.25 | 222.75 |
| H2 | 224.25 | 229.75 |

DEFINITIONS

| Data sheet status | |
|---|---|
| Objective specification | This data sheet contains target or goal specifications for product development. |
| Preliminary specification | This data sheet contains preliminary data; supplementary data may be published later. |
| Product specification | This data sheet contains final product specifications. |
| Application information | |
| Where application information is given, it is advisory and does not form part of the specification. | |

LIFE SUPPORT APPLICATIONS

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.

PURCHASE OF PHILIPS I²C COMPONENTS

Purchase of Philips I²C components conveys a license under the Philips' I²C patent to use the components in the I²C system provided the system conforms to the I²C specification defined by Philips. This specification can be ordered using the code 9398 393 40011.

Philips Components – a worldwide company

Argentina: Ierod, BUENOS AIRES,
Tel. (01) 786 7635, Fax. (01) 786 9397.

Australia: Philips Components Pty Ltd, NORTH RYDE,
Tel. (02) 9805 4455, Fax. (02) 9805 4466.

Austria: Österreichische Philips Industrie GmbH, WIEN,
Tel. (01) 601 01 12 41, Fax. (01) 60 101 12 11.

Belarus: Philips Office Belarus, MINSK,
Tel. (5172) 200 915, Fax. (5172) 200 773.

Benelux: Philips Nederland B.V., EINDHOVEN, NL.,
Tel. (+31 40) 2783 749, Fax. (+31 40) 2788 399.

Brazil: Philips Components, SÃO PAULO,
Tel. (011) 821 2333, Fax. (011) 829 1849.

Canada: Philips Electronics Ltd., SCARBOROUGH,
Tel. (0416) 292 5161, Fax. (0416) 754 6248.

China: Philips Company, SHANGHAI,
Tel. (021) 6485 0600, Fax. (021) 6485 5615.

Colombia: Iprelenso Ltda, SANTAFE DE BOGOTA,
Tel. (01) 345 8713, Fax. (01) 345 8712.

Denmark: Philips Components A/S, COPENHAGEN S,
Tel. (32) 883 333, Fax. (31) 571 949.

Finland: Philips Components, ESPOO,
Tel. 9 (0)-615 800, Fax. 9 (0)-615 80510.

France: Philips Composants, SURESNES,
Tel. (01) 4099 6161, Fax. (01) 4099 6427.

Germany: Philips Components GmbH, HAMBURG,
Tel. (040) 2489-0, Fax. (040) 2489 1400.

Greece: Philips Hellas S.A., TAVROS,
Tel. (01) 4894 339/(01) 4894 239, Fax. (01) 4814 240.

Hong Kong: Philips Hong Kong, KOWLOON,
Tel. 2784 3000, Fax. 2784 3003.

India: Philips India Ltd., BOMBAY,
Tel. (022) 4938 541, Fax. (022) 4938 722.

Indonesia: P.T. Philips Development Corp., JAKARTA,
Tel. (021) 520 1122, Fax. (021) 520 5189.

Ireland: Philips Electronics (Ireland) Ltd., DUBLIN,
Tel. (01) 76 40 203, Fax. (01) 76 40 210.

Israel: Rapac Electronics Ltd., TEL AVIV,
Tel. (03) 6450 444, Fax. (03) 6491 007.

Italy: Philips Components S.r.l., MILANO,
Tel. (02) 6752 2531, Fax. (02) 6752 2557.

Japan: Philips Japan Ltd., TOKYO,
Tel. (03) 3740 5028, Fax. (03) 3740 0580.

Korea (Republic of): Philips Electronics (Korea) Ltd., SEOUL,
Tel. (02) 709 1472, Fax. (02) 709 1480.

Malaysia: Philips Malaysia SDN Berhad
Components Division, PULAU PINANG,
Tel. (04) 657 0055, Fax. (04) 656 5951.

Mexico: Philips Components, EL PASO, U.S.A.,
Tel. (915) 772 4020, Fax. (915) 772 4332.

New Zealand: Philips New Zealand Ltd., AUCKLAND,
Tel. (09) 849 4160, Fax. (09) 849 7811.

Norway: Norsk A/S Philips, OSLO,
Tel. (22) 74 8000, Fax. (22) 74 8341.

Pakistan: Philips Electrical Industries of Pakistan Ltd., KARACHI,
Tel. (021) 587 4641-49, Fax. (021) 577 035/587 4546.

Philippines: Philips Semiconductors Philippines Inc.,
METRO MANILA, Tel. (02) 816 6380, Fax. (02) 817 3474.

Poland: Philips Poland Sp. z.o.o., WARSZAWA,
Tel. (022) 612 2594, Fax. (022) 612 2327.

Portugal: Philips Portuguesa S.A.,
Philips Components: LINDA-A-VELHA,
Tel. (01) 416 3160/416 3333, Fax. (01) 416 3174/416 3366.

Russia: Philips Russia, MOSCOW,
Tel. (095) 247 9124, Fax. (095) 247 9132.

Singapore: Philips Singapore Pte Ltd., SINGAPORE,
Tel. 350 2000, Fax. 355 1758.

South Africa: S.A. Philips Pty Ltd., JOHANNESBURG,
Tel. (011) 470 5911, Fax. (011) 470 5494.

Spain: Philips Components, BARCELONA,
Tel. (93) 301 63 12, Fax. (93) 301 42 43.

Sweden: Philips Components AB, STOCKHOLM,
Tel. (+46) 8 632 2000, Fax. (+46) 8 632 2745.

Switzerland: Philips Components AG, ZÜRICH,
Tel. (01) 488 22 11, Fax. (01) 481 77 30.

Taiwan: Philips Taiwan Ltd., TAIPEI,
Tel. (02) 388 7666, Fax. (02) 382 4382.

Thailand: Philips Electronics (Thailand) Ltd., BANGKOK,
Tel. (02) 745 4090, Fax. (02) 398 0793.

Turkey: Türk Philips Ticaret A.S., GÜLTEPE/ISTANBUL,
Tel. (0212) 279 2770, Fax. (0212) 282 6707.

Ukraine: Philips Ukraine Ltd., KIEV,
Tel. (044) 268 7327, Fax. (044) 268 6323.

United Kingdom: Philips Components Ltd., DORKING,
Tel. (01306) 512 000, Fax. (01306) 512 345.

United States:

- Philips Components, JUPITER, FL,
Tel. (561) 745 3300, Fax. (561) 745 3600.
- For literature: (800) 447 3762.
- Display and Wire Wound Components, ANN ARBOR, MI,
Tel. (313) 996 9400, Fax. (313) 761 2776.
- Magnetic Products, SAUGERTIES, NY,
Tel. (914) 246 2811, Fax. (914) 246 0487.

Uruguay: Philips Components, MONTEVIDEO,
Tel. (02) 704 044, Fax. (02) 920 601.

For all other countries apply to: Philips Components,
Marketing Communications, P.O. Box 218, 5600 MD EINDHOVEN,
The Netherlands, Fax. +31-40-2724 547.

COD11 © Philips Electronics N.V. 1997

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.
The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Printed in The Netherlands

