



Crystal Can Welded • DPDT Magnetic Latching Dry Circuit to 10 Amps

SPECIFICATIONS

GENERAL

Contact Arrangement 2PDT (2 Form C)
Magnetic Latching

Weight 1.6 oz approx.
Designed to meet the requirements of MIL-PRF-39016.

PERFORMANCE

Contact Rating (Note 1):
Resistive 10 Amps @ 28 VDC or 115V 400 Hz
(Case Ungrounded)

Inductive 3.5 Amps @ 28 VDC

Life 100,000 operations minimum
@ rated load, 125°C

Latch/Reset Power:
BR20AX 250 mw approx.
BR20BX 130 mw approx.

Latch/Reset Time 10 ms max, excluding
bounce time at nominal coil voltage

Contact Bounce Time 2 ms max @ 10 Amps
28 VDC

Contact Voltage Drop:
Before Life 100 mv max @ rated current
6 or 28 VDC

After Life 200 mv max @ rated current
6 or 28 VDC

ENVIRONMENTAL

Temperature Range -65°C to +125°C

Vibration (Note 2) 0.4" DA 10 - 38 Hz,
20 G's 38 - 2,000 Hz

Shock (Operating) (Note 2) 50 G's 11 ms

ELECTRICAL CHARACTERISTICS

Duty Cycle Continuous

Insulation Resistance
10,000 megohms @ 500V 25°C
1,000 megohms @ 500V 125°C


Dielectric Strength:
Sea Level:
Between Coils (BR20AX) 500 VRMS
Contact to Case 1,250 VRMS
Contact to Coil 1,250 VRMS
Coil to Case 1,000 VRMS
Across Open Contacts 1,250 VRMS
70,000 Feet
All points 500 VRMS

Notes

- For case grounded loads and other ratings, consult the factory.
- For applications requiring other shock and vibration levels, consult the factory.
- For other ratings consult the factory.
- Relay contacts which have switched high level currents are no longer suitable for switching low level loads.
- Contacts were placed in the position shown by placing voltage with the polarity shown on the indicated coil (reset). To switch contacts, a voltage of indicated polarity must be applied to the other coil (Latch).
- Contacts were placed in position shown by placing voltage with the polarity indicated on the coil. To switch contacts a voltage of the reverse polarity must be applied to the coil.


COIL DATA

PART NUMBER MODEL BR20AX — 10 Amps (Dual Coil, 250 MW) MODEL BR20BX — 10 Amps (Single Coil, 130 MW)		BR20AX-()-V1 BR20BX-()-V1	BR20AX-()-V2 BR20BX-()-V2	BR20AX-()-V3 BR20BX-()-V3	BR20AX-()-V4 BR20BX-()-V4	BR20AX-()-V5 BR20BX-()-V5
NOMINAL COIL VOLTAGE		6 VDC	12 VDC	26 VDC	48 VDC	115 VDC
MAXIMUM COIL VOLTAGE		7.3 VDC	14.8 VDC	32 VDC	59 VDC	127 VDC
LATCH/RESET VOLTAGE (MAX at +125°C)		4.4 VDC	8.4 VDC	18 VDC	33 VDC	79 VDC
LATCH/RESET VOLTAGE (MAX)		3 VDC	6 VDC	13 VDC	24 VDC	57.5 VDC
COIL RESISTANCE ± 10% at 25°C	BR20AX	30 OHMS	120 OHMS	600 OHMS	2200 OHMS	10,000 OHMS
	BR20BX	65 OHMS	250 OHMS	1200 OHMS	4500 OHMS	20,000 OHMS




SCHEMATIC


TERMINAL VIEW



TERMINAL STYLES



MOUNTING CODES



GENERAL NOTES

- Unless otherwise specified, all tests made at nominal coil voltages, @ 25°C.
- For special coil variations, switching configurations, terminals styles and mounting types, consult the factory.
- Unless otherwise specified, tolerances on decimal dimensions are ± .010".
- Specifications contained herein are subject to change without notice.



Microsemi Corporate Headquarters
One Enterprise, Aliso Viejo,
CA 92656 USA

Within the USA: +1 (800) 713-4113
Outside the USA: +1 (949) 380-6100
Sales: +1 (949) 380-6136
Fax: +1 (949) 215-4996

E-mail: sales.support@microsemi.com

© 2015 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.

Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for communications, defense & security, aerospace and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; security technologies and scalable anti-tamper products; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, Calif., and has approximately 3,400 employees globally. Learn more at www.microsemi.com.

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.