

CNZ2152 (ON2152)

Reflective photosensor

Non-contact point SW, object sensing

Overview

CNZ2152 is a photosensor detecting the change of reflective light in which a high efficiency GaAs infrared light emitting diode is used as the light emitting element, and a high sensitivity Si phototransistor is used as the light detecting element. The two elements are located parallel in the same direction and objects are detected when passing in front of the device.

Features

- Fast response
- High sensitivity
- High SN ratio

Applications

- Detection of paper, film and cloth
- Optical mark reading
- Detection of coin and bill
- Detection of position and edge
- Start, end mark detection of magnetic tape

Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit
Input (Light emitting diode)	Reverse voltage	V_R	3 V
	Forward current	I_F	100 mA
	Power dissipation *1	P_D	150 mW
Output (Photo transistor)	Collector-emitter voltage (Base open)	V_{CEO}	20 V
	Emitter-collector voltage (Base open)	V_{ECO}	3 V
	Collector current	I_C	30 mA
	Collector power dissipation *2	P_C	150 mW
	Operating ambient temperature	T_{opr}	-25 to +85 °C
Temperature	Storage temperature	T_{stg}	-30 to +100 °C



Electrical-Optical Characteristics $T_a = 25^\circ\text{C} \pm 3^\circ\text{C}$

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Input characteristics	Forward voltage	V_F $I_F = 100 \text{ mA}$		1.25	1.50	V
	Reverse current	I_R $V_R = 5 \text{ V}$			10	μA
Output characteristics	Collector-emitter cutoff current	I_{CEO} $V_{CE} = 10 \text{ V}$		0.05	2.00	μA
Transfer characteristics	Collector current *1	$V_{CC} = 5 \text{ V}$, $I_F = 20 \text{ mA}$, $R_L = 100 \Omega$	0.8	3.0		mA
				500		μA
	Collector-emitter saturation voltage	$V_{CE(sat)}$ $I_F = 100 \text{ mA}$, $I_C = 1 \text{ mA}$			0.6	V
	Rise time	t_r $V_{CC} = 10 \text{ V}$, $I_C = 1 \text{ mA}$, $R_L = 100 \Omega$		8		μs
	Fall time	t_f		8		μs

Note) 1. Input and output are handled electrically.

2. This product is not designed to withstand radiation


3. *1: Output current measurement circuit (Ambient light is shut off completely)












*2: White paper (reflective ratio 90%)

*3: Tracing paper (paper SM-1 for 2nd original paper)

Note) The part number in the parenthesis shows conventional part number.





Caution for Safety

 **DANGER**

■ This product contains Gallium Arsenide (GaAs).

GaAs powder and vapor are hazardous to human health if inhaled or ingested. Do not burn, destroy, cut, cleave off, or chemically dissolve the product. Follow related laws and ordinances for disposal. The product should be excluded from general industrial waste or household garbage.

Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
 - ☐ Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.

- ☐ If you have any inquiries or questions about this book or our semiconductor products, please contact one of our sales offices listed on the back or Semiconductor Company's Department.