

TENTATIVE

TOSHIBA BIPOLAR LINEAR INTEGRATED CIRCUIT
SILICON MONOLITHIC

TA1231F,TA1231FN

UHF / VHF TUNER IC


The TA1231F and TA1231FN are TV tuner ICs which integrate on a single chip IF amp, a mixer / oscillator for VHF band and cable TV, together with a mixer / oscillator for UHF band. The package is an SSOP16-P-225A (1-mm pitch) or SSOP16-P-225B (0.65-mm pitch) optimal for surface mounting to help make tuners more compact.

FEATURES

- Supply voltage : 9V
- VHF, CATV bands : MIX · OSC
- UHF band : MIX · OSC
- Built-in IF amp
- IF unbalanced output


Note: These devices are easy to be damaged by high static voltage or electric fields.
In regards to this, please handle with care.

TA1231F



SSOP16-P-225-1.00A

TA1231FN



SSOP16-P-225-0.65B

Weight


SSOP16-P-225-1.00A : 0.14g (Typ.)

SSOP16-P-225-0.65B : 0.07g (Typ.)

000707EBA1






- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The products described in this document are subject to the foreign exchange and foreign trade laws.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.

BLOCK DIAGRAM



TERMINAL FUNCTION

PIN No.	PIN NAME	FUNCTION	INTERFACE
1 16	VHF oscillator	VHF oscillator. To prevent abnormal oscillation, connect a resistor between pin 16 and the external capacitor.	
2 3 4 5	UHF oscillator	UHF oscillator. Pin 5 uses both as band switch. Connecting pin 5 to VCC via 22kΩ sets to UHF ; connecting pin 12 to GND sets to VHF. To use VHF SW voltage OPEN rather than GND, connect a resistor of around 10kΩ. Changing capacitor of 6pF connected to pins 2 and 5 of test circuit 2 varies the oscillation frequency range. Be careful not to set the constant too large, because abnormal oscillation may occur.	

PIN No.	PIN NAME	FUNCTION	INTERFACE
6	REG	Regulator output.	
7 8	UHF input	UHF · RF input. Either apply balanced input to pins 7 and 8, or ground pin 7 to AC and apply input to pin 8.	
9 10	VHF input	VHF-RF input. Normally ground pin 10 to AC using a capacitor and input to pin 9.	
11	V _{CC}	V _{CC}	—
12	IF output	IF output. Output impedance : 75Ω	
13 14	MIX output	Mixer output. For turning, connect a tank circuit between pins 13 and 14.	
15	GND	GND	—

MAXIMUM RATINGS (Ta = 25°C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Power Supply Voltage	V _{CC}	11	V
Power Dissipation	P _D	(Note 1)	mW
Operating Temperature	T _{opr}	-20~75	°C
Storage Temperature	T _{stg}	-55~150	°C

Note 1: 641mW for TA1231F

568mW for TA1231FN

When using the device at above Ta = 25°C, decrease the power dissipation F-type by 5.2mW and FN-type by 4.6mW for each increase of 1°C.

The above values are for the IC only. When using the device in an application, take the effect of heat dissipation into consideration.

RECOMMENDED OPERATING CONDITION

PIN No.	SYMBOL	MIN	TYP.	MAX	UNIT
11	V _{CC}	8.1	9.0	9.9	V

ELECTRICAL CHARACTERISTICS

DC CHARACTERISTICS (Unless otherwise specified, V_{CC} = 9V, Ta = 25°C)

CHARACTERISTIC		SYMBOL	TEST CIR-CUIT	TEST CONDITION	MIN	TYP.	MAX	UNIT
Power Supply and Current for VHF		I _{CC-V}	1	—	34	42	52	mA
Power Supply and Current for UHF		I _{CC-U}		—	37	44	56	
Terminal Voltage (*1)	Pin 1 for V	V1-V	1	—	6.5	6.9	7.3	V
	Pin 1 for U	V1-U		—		9		
	Pin 2 for V	V2-V		—	3.3	3.7	4.1	
	Pin 2 for U	V2-U		—	2.9	3.3	3.7	
	Pin 3 for V	V3-V		—	3.7	4.3	4.8	
	Pin 3 for U	V3-U		—	2.1	2.5	2.9	
	Pin 4 for V	V4-V		—		0		
	Pin 4 for U	V4-U		—	2.1	2.5	2.9	
	Pin 5 for V	V5-V		—		0		
	Pin 5 for U	V5-U		—	2.9	3.3	3.7	
	Pin 6 for V	V6-V		—	5.8	6.1	6.4	
	Pin 6 for U	V6-U		—	5.8	6.1	6.4	
	Pin 7 for V	V7-V		—	2.7	3.1	3.5	
	Pin 7 for U	V7-U		—	2.4	2.8	3.2	
	Pin 8 for V	V8-V		—	2.7	3.1	3.5	
	Pin 8 for U	V8-U		—	2.4	2.8	3.2	

CHARACTERISTIC		SYMBOL	TEST CIR-CUIT	TEST CONDITION	MIN	TYP.	MAX	UNIT
Terminal Voltage (*1)	Pin 9 for V	V9-V	1	—	2.4	2.8	3.2	V
	Pin 9 for U	V9-U		—	2.7	3.1	3.5	
	Pin 10 for V	V10-V		—	2.4	2.8	3.2	
	Pin 10 for U	V10-U		—	2.7	3.1	3.5	
	Pin 12 for V	V12-V		—	4.7	5.1	5.5	
	Pin 12 for U	V12-U		—	4.7	5.1	5.5	
	Pin 13 for V	V13-V		—	6.8	7.2	7.6	
	Pin 13 for U	V13-U		—	6.6	7.0	7.4	
	Pin 14 for V	V14-V		—	6.8	7.2	7.6	
	Pin 14 for U	V14-U		—	6.6	7.0	7.4	
	Pin 16 for V	V16-V		—	2.1	2.5	2.9	
	Pin 16 for U	V16-U		—	2.5	2.9	3.3	

* 1: upper : VHF mode
lower : UHF mode

AC CHARACTERISTICS

No.	CHARACTERISTIC	SYMBOL	TEST CIR-CUIT	TEST CONDITION (*2)	MIN	TYP.	MAX	UNIT
1	Conversion Gain	CG	2	VHF-L	22.0	24.5	27.0	dB
				VHF-H	19.0	22.5	26.0	
				UHF	25.0	28.0	31.0	
2	Noise Figure	NF	2	VHF-L	—	11.0	13.0	dB
				VHF-H	—	14.0	17.0	
				UHF	—	11.0	13.0	
3	IF Out Power Level	IFp	2	VHF-L	10.0	13.0	—	dBmW
				VHF-H	10.0	13.0	—	
				UHF	10.0	13.0	—	
4	Conversion Gain Shift	CGs	2	(Note 1) VHF-L	—	—	±1.0	dB
				(Note 1) VHF-H	—	—	±1.0	
				(Note 1) UHF	—	—	±1.0	
5	Frequency Shift	Δf_B	2	(Note 2) VHF-L	—	—	±200	kHz
				(Note 2) VHF-H	—	—	±250	
				(Note 2) UHF	—	—	±250	

No.	CHARACTERISTIC	SYMBOL	TEST CIR- CUIT	TEST CONDITION (*2)		MIN	TYP.	MAX	UNIT
6	Switching On Drift	Δf_s	2	(Note 3)	VHF-L	—	—	± 350	kHz
					VHF-H	—	—	± 350	
					UHF	—	—	± 400	
7	1% Cross Modulation	CM	2	(Note 4)	VHF-L	85.0	89.0	—	dB μ V
					VHF-H	84.0	87.0	—	
					UHF	79.0	83.0	—	
8	Inter Modulation	IM3	2	(Note 5)	VHF-L	-65.0	-70.0	—	dBc
					VHF-H	-65.0	-70.0	—	
					UHF	-65.0	-70.0	—	
9	6-ch Beat	B_6	2	(Note 6)	VHF-L (6ch)	-50.0	-53.0	—	dBc
					VHF-H	—	—	—	
					UHF	—	—	—	

* 2: f_{IF} : 45.75 [MHz]
VHF-L : f_{RF} = 55.25 [MHz]~127.25 [MHz]
VHF-H : f_{RF} = 133.25 [MHz]~367.25 [MHz]
UHF : f_{RF} = 373.25 [MHz]~801.25 [MHz]

TEST CONDITIONS

Note 1: Conversion Gain Shift

Measure conversion gain change when $V_{CC} \pm 10\%$ with input level = -50dBmW , $V_{CC} = 9\text{V}$ as the reference.

Note 2: Frequency Shift

Measure frequency change when $V_{CC} \pm 10\%$ with input level = -40dBmW , $V_{CC} = 9\text{V}$ as the reference.

Note 3: Switching On Drift

Measure frequency change up to 3 minutes with the frequency at 2 seconds after switching on, as the reference. (Input level : -30dBmW)

Note 4: 1% Cross Modulation


- $f_D = f_p$ f_D : Input level = -30dBmW

- $f_{UD} = f_D + 12\text{MHz}$ 100kHz , 30% AM.

Input the two signals above, and increase the f_{UD} input level.

Measure the f_{UD} input level when the suppression level reaches 56.5dB .

(Averaging 10 times using a spectrum analyzer.)



Note 5: Inter Modulation


- $f_D = f_p$

- $f_{UD} = f_D + 1\text{MHz}$

Input the two signals above, and increase the input levels.

When the IF output level is -11dBmW , measure the suppression level.

(Averaging 10 times using a spectrum analyzer.)




Note 6: 6-ch Beat

- $f_p = 83.25\text{MHz}$ (USA : 6ch)
- $f_s = 87.75\text{MHz}$ (USA : 6ch)


Input the two signals above, and increase the input levels.

When the IF output level is -11dBmW , measure the suppression level.


(Averaging 10 times using a spectrum analyzer.)



TEST CIRCUIT 1 DC CHARACTERISTICS



TEST CIRCUIT 2 AC CHARACTERISTICS



	LINE DIAMETER	TURN DIAMETER	NUMBER OF TURNS
L ₁	0.32mm	2.0mm	7.5T
L ₂	0.32mm	1.5mm	2.5T
L ₃	0.32mm	2.5mm	2.5T

L₄ : 0.9μH ± 5%


SW₁—V_{LOW}/V_HI

SW₂—VHF/UHF

PACKAGE DIEMENSIONS

SSOP16-P-225-1.00A

Unit : mm




Weight: 0.14g (Typ.)

PACKAGE DIEMENSIONS

SSOP16-P-225-0.65B

Unit : mm



Weight: 0.07g (Typ.)