

REGISTER CONTROL AND FILAMENT TRANSFORMERS

with single secondary:

50/60 HZ. except *. All with lead terminations except for 21F45, 21F59, 21F61 with lugs.

| S E C T | Part Number | Secondary | | Primary Volts | Insulation Test RMS Volts | Style | Dimensions-Inches | | | | | Wt. Lbs. |
|------------------|----------------|-----------|---------|------------------|------------------------------------|-------|-------------------|----|----|----------|-----|-------------|
| | | RMS | | | | | Case | | | Mounting | | |
| | | Volts | Amps. | | | | H | W | D | MW | MD | |
| A | 21F191 | 2.5CT | .3 | 117 | 1500 | BAH | 1¼ | 2½ | 1⅝ | 1¾ | --- | 0.3 |
| | 21F192 | 2.5 | 1.0 | 117 | 1500 | BAH | 1¾ | 2¾ | 1¾ | 2 | --- | 0.4 |
| | 21F34 | 2.5 | 1.5 | 117 | 2500 | BAH | 1¾ | 2¾ | 1½ | 2¾ | --- | 0.7 |
| | 21F120 | 2.5CT | 3.0 | 115 | 1500 | BAH | 1¾ | 2½ | 1¾ | 2¾ | --- | 0.7 |
| | 21F31 | 2.5CT | 5.0 | 117 | 7500 | BAV | 2¾ | 3¾ | 2½ | 2⅜ | --- | 1.5 |
| | 21F103 | 2.5CT | 10.0 | 107/117 | 7500 | BAV | 3¾ | 3¾ | 2½ | 3½ | --- | 2.5 |
| B | 21F94 | 5.0CT | 3.0 | 115 | 2500 | BAH | 2 | 3¼ | 2½ | 2⅜ | --- | 1.4 |
| | 21F60 | 5.0CT | 6.0 | 115 | 1500 | BAH | 2¼ | 3⅞ | 2¼ | 3½ | --- | 1.7 |
| | 21F105 | 5.0CT | 6.0 | 107/117 | 2500 | BAV | 2¾ | 3¾ | 2½ | 2⅜ | --- | 2.0 |
| | 21F13 | 5.0CT | 10.0 | 117 | 2500 | LAV | 3¾ | 2¾ | 3½ | 2 | 2¾ | 3.5 |
| | 26F66 | 5.0CT | 15.0 | 117 | 2500 | LAV | 3¾ | 2½ | 3 | 2 | 2¼ | 3.0 |
| | 21F07A | 5.0CT | 29.0 | 117 | 2500 | LAV | 3¾ | 3¾ | 3¼ | 2½ | 2½ | 5.9 |
| C | 26F73 | 6.3CT | .3 | 117 | 1500 | BAH | 1¼ | 2½ | 1¾ | 3¼ | --- | 0.3 |
| | 21F162 | 6.3CT | .6 | 117 | 1500 | BAH | 1¾ | 2¾ | 1⅞ | 2 | --- | 0.4 |
| | 21F143 | 6.3CT | 1.0 | 117 | 1500 | BAH | 1¾ | 2¾ | 1⅝ | 2¾ | --- | 0.6 |
| | 21F09 | 6.3CT | 1.2 | 117 | 2500 | BAH | 1¾ | 2¾ | 1¾ | 2¾ | --- | 0.8 |
| | 21F212 | 6.3 | 1.2 | 117 | 2500 | BAH | 1¾ | 2¾ | 1½ | 2¾ | --- | 0.7 |
| | 26F60 | 6.3 | 1.2 | 117 | 7000 | BAH | 2 | 3¼ | 2¼ | 2⅜ | --- | 1.0 |
| D | 21F10 | 6.3CT | 3.0 | 117 | 2500 | BAH | 2 | 3¼ | 2½ | 2⅜ | --- | 1.4 |
| | 21F204 | 6.3CT | 5.0 | 115 | 1500 | BAH | 2¾ | 3¼ | 2¼ | 3½ | --- | 1.8 |
| | #21F59 | 6.3CT | 6.0 | 117 | 2500 | LHV | 3¾ | 2¾ | 2⅞ | 2 | 2 | 2.4 |
| | 21F72 | 6.3CT | 6.0 | 107/117 | 2000 | BAH | 2¾ | 3¾ | 2¾ | 3½ | --- | 2.0 |
| | 21F12 | 6.3CT | 10.0 | 117 | 2500 | LAV | 3¾ | 2½ | 2½ | 2 | 2¼ | 3.0 |
| | #21F43 | 6.3CT | 10.0 | 107/117 | 2500 | LAV | 3½ | 2¾ | 2¾ | 2¼ | 2½ | 3.4 |
| #21F25 | 6.3CT | 20.0 | 107/117 | 2500 | LAV | 4¾ | 3¾ | 3¾ | 3 | 2¾ | 6.7 | |
| E | #21F45 | 7.5CT | 4.0 | 117 | 2500 | LHV | 3¾ | 2¾ | 2⅞ | 2 | 2½ | 2.7 |
| | #21F62 | 7.5CT | 8.0 | 117 | 2500 | LAV | 3¾ | 3¾ | 3 | 2½ | 2¾ | 4.7 |
| | 21F111 | 7.5CT | 21.0 | 107/117 | 2500 | GGV | 4¾ | 3¾ | 4 | 3 | 2⅜ | 8.0 |
| F | 21F205 | 10.0CT | 1.0 | 117 | 1500 | BAH | 2 | 3¼ | 1⅝ | 2⅜ | --- | 0.9 |
| | 26F71 | 10.0CT | 3.0 | 115 | 1500 | BAH | 2¾ | 3¾ | 2¼ | 3½ | --- | 1.6 |
| | 21F207 | 10.0CT | 4.0 | 117 | 1500 | BAH | 2¾ | 4 | 2¼ | 3⅞ | --- | 2.3 |
| | #21F61 | 10.0CT | 4.0 | 117 | 2500 | LHV | 3¾ | 2¾ | 2⅞ | 2¼ | 2 | 3.3 |
| | 21F18 | 10.0CT | 5.0 | 117 | 2500 | LAV | 3¾ | 2¾ | 2½ | 2 | 2 | 2.5 |
| | 21F209 | 10.0CT | 8.0 | 117 | 1500 | LAV | 3¾ | 2¾ | 3½ | 2¼ | 2½ | 4.1 |
| | 21F28 | 10.0CT | 8.0 | 117 | 2500 | LAV | 3¾ | 3¾ | 3¾ | 2½ | 2¾ | 4.9 |
| | 21F112 | 10.0CT | 10.0 | 117 | 2000 | GGV | 3¾ | 3¾ | 3⅞ | 2½ | 2¾ | 5.2 |
| 21F173 | 10.0CT | 10.0 | 117 | 2000 | LAV | 4¾ | 3½ | 3¼ | 2¾ | 2¾ | 7.5 | |
| G | 23V252 | 12.0 | .15 | 117 | 1500 | BAH | 1¼ | 2½ | 1¼ | 1¾ | --- | 0.3 |
| | 23V253 | 12.0 | .35 | 117 | 1500 | BAH | 1¾ | 2¾ | 1⅞ | 2 | --- | 0.4 |
| | 23V254 | 12.0 | .70 | 117 | 1500 | BAH | 1¾ | 2¾ | 1¾ | 2¾ | --- | 0.6 |
| | 23V255 | 12.0 | 1.2 | 117 | 1500 | BAH | 2 | 3¼ | 1¾ | 2⅜ | --- | 0.9 |
| | 23V415 | 12.0 | 2.0 | 117 | 1500 | BAH | 2 | 3¼ | 2½ | 2⅜ | --- | 1.3 |
| | 23V416 | 12.0 | 4.0 | 117 | 1500 | BAH | 2¾ | 4 | 2¼ | 3⅞ | --- | 2.3 |
| | 23V417 | 12.0 | 6.0 | 117 | 1500 | LAV | 3¾ | 2¾ | 2¾ | 2¼ | 2½ | 3.4 |
| | 23V418 | 12.0 | 8.0 | 117 | 1500 | LAV | 3¾ | 3¾ | 2¾ | 2½ | 2½ | 4.3 |

Has electrostatic shield.

