



Weight: 145.29 g

Suitable Cables: LDF4-50A; RF1/2"BHF

This part number complies with RoHS.

Notice: JYEBAO reserves the right to make modifications deemed appropriate.



CABLE ASSEMBLY INSTRUCTION 7/16-3200B-1/2A JYE BAO CO., LTD. В С D BODY O-RING NUT O-RING DIAGRAM ASSEMBLY INSTRUCTION 40.8 [1.608] Step 1: STRIP AS SHOWN. Step 2: PUT VASELINE ON " D " AND SLIDE O-RING " D " OVER CABLE . Step 3: SHARPEN CENTER CONDUCTOR TIP. SHARPEN -Step 4: SLIDE NUT " C " OVER CABLE. Step 5: PUT VASELINE ON " B " AND SLIDE O-RING " B " OVER THE NUT " C " . СВ Step 6: FINALLY SCREW " C " ON THE CONNECTOR

This part number complies with RoHS.

Notice: JYEBAO reserves the right to make modifications deemed appropriate.