

Yagi Antennas (806-960 MHz)

Model Number	Frequency (MHz)	Gain (dBd)	Number of Elements	Beamwidth (E) / (H)	Power (watts)	Wind Rating MPH/(kph)	Suggested List Price
850- 3	806-896	5	3	68/121	50	150/240	93.10
835- 4	806-866	7	4	60/84	50	150/240	99.10
860- 4	824-896	7	4	60/84	50	150/240	99.10
890- 4	806-960	5	4	64/99	50	150/240	99.10
835- 6	806-866	9	6	49/59	50	150/240	111.75
860- 6	824-896	9	6	49/59	50	150/240	111.75
835- 8	806-866	10	10	43/50	50	150/240	127.60
860- 8	824-896	10	10	43/50	50	150/240	127.60
835- 10	806-866	12	10	37/41	50	150/240	140.85
860- 10	824-896	12	10	37/41	50	150/240	140.85
918- 2	902-928	4	2	71/140	50	150/240	87.50
918- 3	902-928	5	3	70/130	50	150/240	93.10
918- 4	902-928	7	4	57/78	50	150/240	99.10
918- 6	902-928	9	6	49/59	50	150/240	111.75
918- 10	902-928	12	10	34/36	50	150/240	140.85
918- 15	902-928	13	15	30/32	50	125/200	193.65
918- 2LAN	902-928	4	2	71/140	50	150/240	87.50
918- 3LAN	902-928	5	3	70/130	50	150/240	93.10
918- 4LAN	902-928	7	4	57/78	50	150/240	99.10
918- 6LAN	902-928	9	6	49/59	50	150/240	111.75
918- 10LAN	902-928	12	10	34/36	50	150/240	140.85
918- 15LAN	902-928	13	15	30/32	50	125/200	193.65
928- 3	896-960	5	3	73/130	50	150/240	93.10
928- 4	896-960	7	4	58/81	50	150/240	99.10
928- 6	896-960	9	6	49/59	50	150/240	111.75
944- 7	928-960	10	7	45/52	50	150/240	121.35
920- 10	896-940	12	10	34/36	50	150/240	140.85
944- 10	928-960	12	10	37/40	50	150/240	140.85
944- 15	928-960	13	15	30/32	50	125/200	193.65

(LAN systems are matched to 75 ohms)

Antennaco's Yagi antennas utilize our unique EverSealed feed system to protect the feed assembly from failure due to moisture and corrosion. We've also eliminated the need for field tuning, making installation fast and dependable.