


LC7464M

Infrared Remote Control Transmitter IC

Preliminary

Overview

The LC7464M is a 64-key infrared remote control transmitter IC that incorporates all key-scanning, oscillator and timing function on-chip, resulting in a very low external component count.

The LC7464M generates 71 function codes using the 64 function keys. The output data format comprises the mask-programmed custom code, the parity field, the mask-programmed system code, the product code, the function code and the data check code.

The LC7464M operates from a 2.0 to 3.6 V supply and is available in 24-pin MFPs.


Features

- Low external component count.
- 64 function keys.
- 71 function codes.
- Mask-programmable custom and system codes.
- 64 product codes.
- Output conforms to Japan's Association for Electric Home Appliances recommended standards for infrared remote controls.
- On-chip input pull-down resistors.
- 2.0 to 3.6 V supply.
- 24-pin MFP.


Package Dimensions

unit:mm

3045B-MFP24



Pin Assignment



■ Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.


■ SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

SANYO Electric Co.,Ltd. Semiconductor Company

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

LC7464M

Block Diagram



Pin Description

Number	Name	Equivalent circuit	Description
1 to 6, 23, 24	K10 to K17		Keyswitch scanning inputs
7	REM		LED driver output
8	V _{DD}		Supply voltage
9	TEST		Test input. TEST should be tied HIGH or left open for normal operation
10	OSC1		Ceramic oscillator input connection
11	OSC2		Ceramic oscillator output connection
12	V _{SS}		Ground
13, 14	GCL, GCH		Product code select inputs
15 to 22	KO0 to KO7		Keyswitch scanning outputs

LC7464M

Specifications

Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Supply voltage	$V_{DD\text{ max}}$		$V_{SS}-0.3$ to $+5.5$	V
Input voltage range	V_I		$V_{SS}-0.3$ to $V_{DD}+0.3$	V
Output voltage range	V_O		$V_{SS}-0.3$ to $V_{DD}+0.3$	V
Output current	I_O		-35	mA
Power dissipation	$P_d\text{ max}$	$T_a \leq 85^\circ\text{C}$	150	mW
Operating temperature range	T_{opr}		-40 to $+85$	$^\circ\text{C}$
Storage temperature range	T_{stg}		50 to $+125$	$^\circ\text{C}$

Recommended Operating Conditions at $T_a = -40$ to $+85^\circ\text{C}$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply voltage	V_{DD}		2.0	3.0	3.6	V
KI0 to KI7, GCL and GCH high-level input voltage	V_{IH}		$0.7V_{DD}$		V_{DD}	V
KI0 to KI7, GCL and GCH low-level input voltage	V_{IL}		V_{SS}		$0.3V_{DD}$	V
Oscillator frequency	f_{OSC}		433	455	477	kHz

Electrical Characteristics at $T_a = -40$ to $+85^\circ\text{C}$, $V_{DD} = 2.0$ to 3.6 V

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Operating supply current	I_{DD}	Key pressed, no load			1	mA
Standby supply current	I_{DS}	No Key pressed, oscillator stopped			1	μA
REM high-level output current	I_{OH}	$V_{DD}=2\text{V}, V_{OH}=V_{DD}-1\text{V}$ $V_{DD}=3\text{V}, V_{OH}=V_{DD}-1\text{V}$		-2.5 -11		mA
KO0 to KO7 high-level output voltage	V_{OH}	$I_{OH}=0.1\text{mA}$	$V_{DD}-0.3$			V
KO0 to KO7 and REM low-level output voltage	V_{OL}	$I_{OL}=0.1\text{mA}$			0.3	V
GCL and GCH high-level input current	I_{IH}	$V_I=V_{DD}$			1	μA
GCL and GCH low-level input current	I_{IL}	$V_I=V_{SS}$	-1			μA
KI0 to KI7 input floating voltage	V_{IF}				$0.1V_{DD}$	V
KI0 to KI7 input pull-down resistance	R_{iN}		75	100	125	$\text{k}\Omega$

DISCONTINUED PRODUCT

Functional Description

Key Inputs

An eight-by-eight matrix is formed with the keyswitch scanning outputs KO0 to KO7 and the keyswitch scanning inputs KI0 to KI7 as shown in the following figure. When a key is held down, either the normal or abbreviated continuation code is output continuously, depending on the mask option selected.

Normally, only one key can be pressed at a time. If more than one key is pressed, all keys are ignored and no output is generated. However, when the appropriate mask option is selected, up to three extra codes can be generated by holding down key 8 and either key 16, 24, 32, 40, 48, 56 or 64 as shown in table 1.


	KI0	KI1	KI2	KI3	KI4	KI5	KI6	KI7
KO0	1	9	17	25	33	41	49	57
KO1	2	10	18	26	34	42	50	58
KO2	3	11	19	27	35	43	51	59
KO3	4	12	20	28	36	44	52	60
KO4	5	13	21	29	37	45	53	61
KO5	6	14	22	30	38	46	54	62
KO6	7	15	23	31	39	47	55	63
KO7	8	16	24	32	40	48	56	64

Table 1. Function code generation

Key combination	Function code							
	FC0	FC1	FC2	FC3	FC4	FC5	FC6	FC7
8, 16	1	1	1	0	1	0	0	1
8, 24	1	1	1	0	0	1	0	1
8, 32	1	1	1	0	1	1	0	1
8, 40	1	1	1	0	0	0	1	1
8, 48	1	1	1	0	1	0	1	1
8, 56	1	1	1	0	0	1	1	1
8, 64	1	1	1	0	1	1	1	1

Output Data Configuration

The 48-bit output data configuration is shown in the following figure. Note that the data is sent least-significant bit first.



Custom code

The 16-bit mask-programmable custom code (C0 to C15) is a unique code registered with the Association for Electric Home Appliances.

Parity bits

The four parity bits (P0 to P3) are used for error detection. Their value is given by the following equation.

$$P_n = C_n \oplus C_{n+4} \oplus C_{n+8} \oplus C_{n+12}$$


where n=0 to 3.

System code

The four-bit system code (SC0 to SC3) is mask-programmed into the LC7464M during fabrication.

Product code

The eight-bit product code (GC0 to GC7) consists of two mask-programmable bits and six bits that are set by connecting each of GCL and GCH to one of KO0 to KO7. The block diagram of the product code generator is shown in the following figure. GC1 and GC3 are the mask-programmable bits, shown set to zero.



LC7464M

Tables 2 and 3 show the relationships between GCL and L0 to L2, and between GCH and H0 to H2, respectively.

Table 2. GCL product codes

Pin	Code generated		
	L0	L1	L2
KO0	0	0	0
KO1	1	0	0
KO2	0	1	0
KO3	1	1	0
KO4	0	0	1
KO5	1	0	1
KO6	0	1	1
KO7	1	1	1

Table 3. GCH product codes

Pin	Code generated		
	H0	H1	H2
KO0	0	0	0
KO1	1	0	0
KO2	0	1	0
KO3	1	1	0
KO4	0	0	1
KO5	1	0	1
KO6	0	1	1
KO7	1	1	1

Function code

The eight-bit function code (FC0 to FC7) is determined by the number of the key pressed as shown in the following figure. Note that when the appropriate mask option is selected, function codes 97H, A7H, B7H, C7H, D7H, E7H and F7H can be generated by holding down key 8 and one of keys 16, 24, 32, 40, 48, 56 and 64.

		Upper-level code (corresponds to KI)															
		0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
Lower-level code (corresponds to KO)	0	[Shaded area]															
	1																
	2																
	3																
	4																
	5																
	6																
	7																
8	[Shaded area]																
9																	
A																	
B																	
C																	
D																	
E																	
F																	

Data check code

The eight-bit data check code (DC0 to DC7) is generated by adding the carry bits from the system code to the product and function code bits. This code is used for error detection. The data check code is calculated using the following equation.

$$DC = SC + GC_0 \text{ to } GC_3 + GC_4 \text{ to } GC_7 + FC_0 \text{ to } FC_3 + FC_4 \text{ to } FC_7$$


For example, when

$$SC = 0H, GC = 0B1H, FC = 35H$$


$$DC = 0H + 1H + 0BH + 5H + 3H = 14H$$

Data Transmission Waveforms

Abbreviated transmission mode




Abbreviated mode detail




LC7464M

Normal transmission mode





Oscillator

The LC7464M contains a self-biasing CMOS inverter that is used as an oscillator when connected to a ceramic resonator as shown in the following figure. To reduce power, the oscillator operates only when a key is pressed.



Typical Application



- 
- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
 - SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
 - In the event that any or all SANYO products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
 - No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
 - Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
 - Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 2001. Specifications and information herein are subject to change without notice.