

SMA - 306 Style (SMA-306) Transmitters and Receivers

T-41-91

The SMA-306 style devices consist of a Base Part mounted in a Metal SMA-306 connector. LEDs and receivers are assembled to insure the best power output or responsivity for each dash number. All output power, responsivity, and sensitivity limits are those of the base part. See the dash number (-XXX) of the base part for the proper limits. For information on the Base Part see pages 15 & 16 for transmitters and pages 16 & 17 for receivers in this Selection Guide.

LEDs

Part #	Description	Base Part	Pinout			
			1	2	3	4
HFE4831 -XXX	5 to 30 μ W @ 100mA into 50/125 micron cable.	HFE4000	A	K	G	N
HFE4842 -XXX	15 to 30 μ W @ 50mA into 100/140 micron cable.	HFE4020	A	K	N	N
HFE4853 -XXX	5 to 30 μ W @ 100mA into 50/125 micron cable.	HFE4003	A	K	G	N
HFE4864 -XXX	15 to 30 μ W @ 50 mA into 100/140 micron cable.	HFE4023	A	K	N	N

Digital Integrated Transmitters ($V_{cc}=5.0V$)

Part #	Description	Base Part	Pinout			
			1	2	3	4
HFE4852 -XXX	10Mbps, 2.5 to 20 μ W into 50/125 micron cable.	HFE4010	V	I	G	N

PhotoDiodes

Part #	Description	Base Part	Pinout			
			1	2	3	4
HFD3867 -XXX	0.45 A/W, $I_D < 2.0nA$ @ $V_R = 5V$, $B_{VR} > 110V$.	HFD3002	A	K	G	N
HFD3868 -XXX	0.45 A/W, $I_D < 2.0nA$ @ $V_R = 5V$, $B_{VR} > 110V$.	HFD3022	A	K	G	N

Digital Integrated Receivers ($V_{cc}=5.0V$)

Part #	Description	Base Part	Pinout			
			1	2	3	4
HFD3872 -XXX	Differentiating, 10Mbps, 1.0 μ W	HFD3000	V	O	G	N
HFD3873 -XXX	Differentiating, 10Mbps, 1.0 μ W	HFD3020	C	V	O	G

Package Information - SMA-306 style

All dimensions are in inches.

Pinout Definition
A = Anode
C = Capacitor
G = Ground (Case)
I = Input
K = Cathode
N = Not Used
O = Output
V = +V (V_{cc})

