

# UNIUNCTION TRANSISTORS

Item Number	Part Number	Manufacturer	P <sub>D</sub> Max (W)	Intrinsic Standoff Ratio		I <sub>P</sub> Max (A)	I <sub>V</sub> Max (A)	Interbase Resistance		V <sub>B2B1</sub> Max (V)	Operating Temperature		Package Style
				Min	Max			Min (Ohms)	Max		Min	Max (°C)	
<b>PN (N-Type Base), (Cont'd)</b>													
-	2N490B	See Index	450m	0.51	0.62	6.0u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N489	See Index	450m	0.51	0.62	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N489A	See Index	450m	0.51	0.62	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N490	See Index	450m	0.51	0.62	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5
5	2N490A	See Index	450m	0.51	0.62	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N2213	Space Power	450m	0.56	0.68			4.7k	9.1k	40	-60	140	Can
-	2N2213	Swampscott	450m	0.56	0.68			4.7k	9.1k	40	-60	140	Can
-	2N492C	See Index	450m	0.56	0.68	2.0u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N491B	See Index	450m	0.56	0.68	6.0u	8.0m	4.7k	6.8k	65	-65	140	TO-5
10	2N492B	See Index	450m	0.56	0.68	6.0u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N491	See Index	450m	0.56	0.68	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N491A	See Index	450m	0.56	0.68	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N492	See Index	450m	0.56	0.68	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N492A	See Index	450m	0.56	0.68	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5
15	2N494C	See Index	450m	0.62	0.75	2.0u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N493B	See Index	450m	0.62	0.75	6.0u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N494B	See Index	450m	0.62	0.75	6.0u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N493	See Index	450m	0.62	0.75	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
-	2N493A	See Index	450m	0.62	0.75	12u	8.0m	4.7k	6.8k	65	-65	140	TO-5
20	2N494	See Index	450m	0.62	0.75	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5
-	2N494A	See Index	450m	0.62	0.75	12u	8.0m	6.2k	9.1k	65	-65	140	TO-5

## Need Surface-Mount Semiconductors?

The complete D.A.T.A. DIGEST library contains information dedicated to surface mount technology.

### DISCRETE SEMICONDUCTORS

DIODES DIGEST

TRANSISTORS DIGEST

THYRISTORS DIGEST

POWER SEMICONDUCTORS DIGEST

### IC SEMICONDUCTORS

LINEAR ICs DIGEST

DIGITAL ICs DIGEST

MEMORY ICs DIGEST

INTERFACE ICs DIGEST

MICROPROCESSOR ICs DIGEST

### SPECIAL DEVICES & DIRECTORIES

OPTOELECTRONICS DIGEST

APPLICATIONS NOTES DIGEST