



**Description**  
BNC 75 Ohm Receptacle Jack -  
Printed Circuit Board Right-Angle

<b>Ordering Data</b>									
<b>BNC 75 Ohm Receptacle Jack - Printed Circuit Board Right-Angle</b>									
Part Number	Dimension						Finish	Mtg. PCB	Note
	A		B		C				
	mm	in.	mm	in.	mm	in.			
28JR401-1	10.97	0.432	3.33	0.131	28.02	1.103	Nickel	B7	
28JR401-2	10.97	0.432	3.33	0.131	28.02	1.103	Tri-Alloy	B7	
28JR404-1	10.97	0.432	3.33	0.131	28.02	1.103	Nickel	B7	1
28JR521-1	10.97	0.432	3.33	0.131	28.02	1.103	Nickel	B5	

Note 1 - Short Insulator



**Description**  
BNC 75 Ohm Receptacle Jack -  
Single Hole Mount Straight

<b>Ordering Data</b>							
<b>BNC 75 Ohm Receptacle Jack - Single Hole Mount Straight</b>							
Part Number	Dimension				Finish	Mtg. Hole	Note
	A		B				
	mm	in.	mm	in.			
28JR217-2	24.21	0.953	13.10	0.516	Nickel	Threaded 3/8-32	
28JR261-1	32.94	1.297	15.08	0.594	Silver	DD2	
28JR268-1	26.99	1.063	13.89	0.547	Nickel	D8	
28JR343-1	20.24	0.797	11.91	0.469	Nickel	D8	
28JR345-1	20.24	0.797	15.88	0.625	Nickel	D5	Reverse Mount



**Description**  
BNC 75 Ohm Receptacle Jack -  
Flange Mount Solder Straight

<b>Ordering Data</b>						
<b>BNC 75 Ohm Receptacle Jack - Flange Mount Solder Straight</b>						
Part Number	Dimension				Finish	Mtg. Plate
	A		B			
	mm	in.	mm	in.		
28JR258-1	24.21	0.953	15.88	0.625	Nickel	3B