

NPN TRANSISTORS

IC Amps Max	V _{CE0} (sus) Volts Min	Device Type	hFE @ IC		ft MHz	Watts	PD @ TC °C	Case JEDEC	
			Min	Amps					
2	80	2N4300	15	2.0	30	15	100	T0-5	
		2N4998	30	1.0	50	30	25	T0-111	
		2N5000	70	1.0	60	30	25	T0-111	
3	150	SFT4300	50	2.0	100	15	100	T0-5	
	40	2N3867	25	2.5	60	6	25	T0-5	
	60	2N5334	30	1.0	40	6	25	T0-39	
	80	2N5335	30	1.0	40	6	25	T0-39	
	150	SFT3507	30	3.0	60	5	25	T0-5	
5	80	2N5152	30	2.5	60	10	50	T0-5	
		2N5154	70	2.5	70	10	50	T0-5	
		2N3996	40	1.0	40	30	100	T0-111	
		2N3997	80	1.0	40	30	100	T0-111	
		SFT3997	80	1.0	80	30	100	T0-59	
		2N5336	30	2.0	30	6	25	T0-39	
		2N5337	30	2.0	30	6	25	T0-39	
		2N5002	30	2.5	60	50	50	T0-59	
		2N5004	70	2.5	70	50	50	T0-59	
		2N5338	30	2.0	30	6	25	T0-5	
		2N5339	60	2.0	30	6	25	T0-5	
		SFD5390 †	1000	5.0	40	15	15	100	T0-33
		SFT502	30	2.5	80	10	10	50	T0-5
		SFT504	50	2.5	80	10	10	50	T0-5
10	80	2N5006	30	5.0	35	100	50	T0-61	
		2N5008	70	5.0	40	100	50	T0-61	
		2N5659	50	5.0	30	30	100	T0-111	
		SFT6200	50	5.0	100	10	25	T0-5	
15	150	SFT5659	50	5.0	70	30	25	T0-59	
20	90	2N3265	20	15	20	125	25	T0-63	
30	90	2N5330	40	10	80	80	100	T0-61	
	120	SFT5671	20	30	30	150	25	T0-3*	
	140	SFT5672	20	30	30	150	25	T0-3*	
	200	2N6322	6	30	10	200	100	T0-3	
50	120	2N6324	6	30	10	200	100	T0-63	
	140	SFT5671	10	50	50	150	25	T0-3*	
90	140	SFT5672	10	50	50				
	140	SFT815	15	90	10	300	50	T0-3*	
100	100	SFT1010	7	100	35	300	50	T0-3*	
	120	SFT1012	7	100	35	300	50	T0-3*	
	140	SFT1014	7	100	35	300	50	T0-3*	
	150	SFT1002	10	50	50	200	25	T0-3*	
		SFT1004	25	50	50	200	25	T0-3*	
	160	SFT1016	7	100	40	300	50	T0-3*	
	180	SFT1018	7	100	40	300	50	T0-3*	
	200	SFT1020	7	100	40	300	50	T0-3*	
	100	SFT2010	5	200	30	600	50	T0-3*	
	120	SFT2012	5	200	30	600	50	T0-3*	
200	140	SFT2014	5	200	30	600	50	T0-3*	

Contact SSDI for higher voltage units.

* TO - 3 with 60 Mil Pins

†Darlington