

PRODUCTS

Chilisin provides inductor turnkey solutions for EMI, power and RF and a global technical team to support its customers. Chilisin has become one of the few inductor suppliers capable of providing a complete "one-stop shopping" experience.



MHCB06030

Home > Products > Power Inductor > MHCB06030

- Power Inductor
- Chip Inductor
- Bead
- Common Mode Choke
- ◆ Product Search



Part Number : MHCB06030-100M-C1

Structure	Closed Magnetic Circuit Type- Molding Processing & for Ultra High Current
Inductance(?H)	10
Tolerance(±%)	20
Test Frequency	100kHz,0.5V
RDC(?)Max	0.102
Isat(A)Typ	7
Irms(A)Typ	3
Operating Temperature	- 5 5 °C ~ 1 2 5 °C (Including self - temperature rise)
L(mm)	6.6±0.2
W(mm)	6.95±0.35
T(mm)	2.8±0.2

- 1.Irms DC current (A) that will cause an approximate ?T of 40°C.
- 2.Isat DC current (A) that will cause Lo to drop approximately 30%

P/N	MHCB06030-100M-C1
Part Numbering	
Dimensions	
Packing	
Recommended Pattern	
Electrical Characteristics Curve	

Back