

Products

- » SMPTE Fiber Products
- » 12G-SDI Products
- » Cables
- » Connectors
- » Video Patchbays and Panels
- » EO/OE Systems
- » Cable Assemblies
- » Cable Reels
- » Tools

- Distributor Listing
- Catalog
- Tech Notes
- FAQ

▶ **75 ohm DIN 1.0/2.3 PCB Mount Receptacles (DCJ-LR, DCJ-LR/1, DCJ-FEM)**



Product Image

Product Name
75 ohm DIN 1.0/2.3 PCB Mount Receptacles

Model Number
DCJ-LR, DCJ-LR/1, DCJ-FEM


PCB Mount Receptacle

VSWR 1.2@3GHz

Model	Description	Nut Driver Bolt
DCJ-LR	Right Angle	NDT-DIN
DCJ-LR/1	Right Angle, Long type	NDT-DIN
DCJ-FEM	Edge Mount	NDT-DIN


*Standard Package (20pcs/100pcs)

- Compact design ideal for high density mounting and downsizing devices.
- Combination of DCJ-LR/1 and DCJ-FEM will be effective for staggered arrangement.
- Return loss: 20dB or greater up to 3GHz.



- Return loss: 20 dB or greater up to 3GHz.
- Combination of DCJ-LR/1 and DCJ-FEM is ideal for high density mounting.
- Nut driver bit NDT-DIN is required for the Receptacle.

<Panel Hole Dim.>



<PCB Hole Dim.>

