


N 75 Ohm Cable Plugs

Description

N 75 Ohm Cable Plug - Straight Cut Straight




Ordering Data

N 75 Ohm Cable Plug - Straight Cut Straight

Part Number	Cable RG-/U	Dimension				Finish	Assembly Instructions	Note
		A		B				
		mm	in.	mm	in.			
25P164-1	59	34.93	1.375	12.70	0.500	Nickel	AI-258	Clamp Cable Termination
25P165-1	59, 62	34.93	1.375	12.70	0.500	Silver	AI-12	
25P171-1	216	38.10	1.500	19.05	0.750	Nickel	AI-81	
25P171-2	11, Belden 8238	38.10	1.500	19.05	0.750	Nickel	AI-81	

Description

N 75 Ohm Cable Plug - Straight Cut Right-Angle




Ordering Data

N 75 Ohm Cable Plug - Straight Cut Right-Angle

Part Number	Cable RG-/U	Dimension						Finish	Assembly Instructions
		A		B		C			
		mm	in.	mm	in.	mm	in.		
25P172-1	216	34.93	1.375	40.48	1.594	19.05	0.750	Nickel	AI-81

Description

N 75 Ohm Cable Jack - Single Hole Mount Clamp Straight



Ordering Data

N 75 Ohm Cable Jack - Single Hole Mount Clamp Straight

Part Number	Cable RG-/U	Dimension						Finish	Mtg. Hole	Assembly Instructions
		A		B		C				
		mm	in.	mm	in.	mm	in.			
25JS111-1	59, 62	41.67	1.641	12.70	0.500	23.42	0.922	Silver	DD1	AI-301
25JS137-1	187, 179	41.67	1.641	12.70	0.500	23.42	0.922	Nickel	DD1	AI-159