

## MINIATURE RELAY


# 1 POLE—1 A (FOR SIGNAL SWITCHING)

## SY SERIES

**RoHS** compliant

#### **■ FEATURES**

- Very small size and light weight
- UL, CSA recognized
- Conforms to FCC rules and regulations part 68
  - —Dielectric strength 1000 VAC between coil and contacts
  - -Surge strength 1500 V
- High sensitivity
- Wide ambient temperature range (-30°C to +90°C)
- Wide operating range
- · DIL pitch terminals
- · Plastic sealed type
- Dial-pulse relay available (10pps, 20pps)
- RoHS compliant since date code: 0519 Please see page 5 for more information



#### ORDERING INFORMATION

[Example]  $\frac{SY}{(a)} - \frac{12}{(b)} \frac{W}{(c)} - \frac{K}{(d)}$ 

(a)	Series Name	SY: SY Series
(b)	Nominal Voltage	Refer to the COIL DATA CHART
(c)	Contact	Nil: Single type W: Bifurcated type
(d)	Enclosure	K: Plastic sealed type

Note: For movable and stationary contact with gold overlay type, add suffix "-OH"

#### SAFETY STANDARD AND FILE NUMBERS

UL478, 508 (File No. E45026)

C22.2 No. 14 (File No. LR35579)

Please request when the approval markings are required on the cover.

Nominal voltage	Contact rating			
1.5 to 24 VDC	0.5 A 1 A 0.15 A	120 VAC ———————————————————————————————————		

1

#### ■ SPECIFICATIONS

	Item		SY-( ) -K (Single)	SY-( ) W - K (Bifurcated)		
Contact	Arrangement		1 form C (SPDT)			
	Material		Gold overlay silver alloy			
	Resistance (initial)		Maximum 100 mΩ (at 1 A 6 VDC)			
	Rating (resistive)		0.5 A 120 VAC or 1 A 24 VDC			
	Maximum (	Carrying Current	2 A			
	Maximum S	Switching Power	60 AV, 24 W			
	Maximum S	Switching Voltage	120 VAC/60 VDC			
	Maximum Switching Current		1 A			
	Minimum Switching Load*1		1 mA 1 VDC	0.1 mA 100 mVDC		
	Capacitance (at 10 MHz)		Approximately 1.4 pF (between open contacts) Approximately 5.0 pF (between coil and contacts)			
Coil	Nominal Power (at 20°C)		0.15 to 0.175 W			
	Operate Power (at 20°C)		0.075 to 0.086 W			
	Operating Temperature		-30°C to +90°C (no frost)/18 V coil: +85°C, 24 V coil: +80°C			
Time Value	Operate (at nominal voltage)		Maximum 5 ms			
	Release (at nominal voltage)		Maximum 2 ms			
Insulation	Resistance		Minimum 1,000 MΩ (at 500 VDC)	Minimum 1,000 MΩ (at 250 VDC)		
	Dielectric strength	between open contacts	400 VAC 1 minute	300 VAC 1 minute		
		between coil and contacts	1,000 VAC 1 minute			
	Surge Strength		1,500 V			
Life	Mechanical		5 × 10 <sup>6</sup> operations minimum			
	Electrical (at contact rating)		1 × 10 <sup>5</sup> operations minimum	1 × 10 <sup>5</sup> operations minimum		
Other	Vibration	Misoperation	10 to 55 Hz (double amplitude of 1.5 mm)			
	Resistance	Endurance	10 to 55 Hz (double amplitude of 1.5 mm)			
	Shock	Misoperation	300 m/s <sup>2</sup> (11 ±1 ms)			
	Resistance	Endurance	1,000 m/s <sup>2</sup> (6 ±1 ms)			
	Weight		Approximately 1.7 g			

<sup>\*1</sup> Minimum switching loads mentioned above are reference values. Please perform the confirmation test with the actual load before production since reference values may vary according to switching frequencies, environmental conditions and


#### **■ COIL DATA CHART**

MODEL		Nominal	Coil resistance	Must operate	Must release	Nominal
Single	Bifurcated	voltage	(±10%)	voltage	voltage	power
SY-1.5-K	SY-1.5W-K	1.5 VDC	15 Ω	1.05 VDC	0.08 VDC	150 mW
SY- 3-K	SY- 3 W-K	3 VDC	60 Ω	2.1 VDC	0.15 VDC	150 mW
SY-4.5-K	SY-4.5W-K	4.5 VDC	135 Ω	3.2 VDC	0.23 VDC	150 mW
SY- 5-K	SY- 5 W-K	5 VDC	167 Ω	3.5 VDC	0.25 VDC	150 mW
SY- 6-K	SY- 6 W-K	6 VDC	240 Ω	4.2 VDC	0.3 VDC	150 mW
SY- 9-K	SY- 9 W-K	9 VDC	540 Ω	6.3 VDC	0.45 VDC	150 mW
SY-12 -K	SY-12 W-K	12 VDC	960 Ω	8.4 VDC	0.6 VDC	150 mW
SY-18 -K	SY-18 W-K	18 VDC	1,940 Ω	12.6 VDC	0.9 VDC	170 mW
SY-24 -K	SY-24 W-K	24 VDC	3,290 Ω	16.8 VDC	1.2 VDC	175 mW

Note: All values in the table are measured at 20°C.

10 20 30 40 50 Contact Voltage(V)

#### ■ CHARACTERISTIC DATA




1.0


Contact Current(A)

## **SY SERIES**

#### ■ REFERENCE DATA



#### **■ DIMENSIONS**



Unit: mm

### RoHS Compliance and Lead Free Relay Information

#### 1. General Information

- Relays produced after the specific date code that is indicated on each data sheet are lead-free
  now. Most of our signal and power relays are lead-free. Please refer to Lead-Free Status Info.
  (http://www.fujitsu.com/us/downloads/MICRO/fcai/relays/lead-free-letter.pdf)
- Lead free solder paste currently used in relays is Sn-3.0Ag-0.5Cu.
- All signal and most power relays also comply with RoHS. Please refer to individual data sheets. Relays that are RoHS compliant do not contain the 5 hazardous materials that are restricted by RoHS directive (lead, mercury, chromium IV, PBB, PBDE).
- It has been verified that using lead-free relays in leaded assembly process will not cause any problems (compatible).
- "LF" is marked on each outer and inner carton. (No marking on individual relays).
- To avoid leaded relays (for lead-free sample, etc.) please consult with area sales office.
- We will ship leaded relays as long as the leaded relay inventory exists.

Note: Cadmium was exempted from RoHSon October 21, 2005. (Amendment to Directive 2002/95/EC)

#### 2. Recommended Lead Free Solder Profile

Recommended solder paste Sn-3.0Ag-0.5Cu.

#### **Reflow Solder condtion**

#### Flow Solder condtion:

Pre-heating: maximum 120°C dip within 5 sec. at 260°C soler bath

#### Solder by Soldering Iron:

Soldering Iron

Temperature: maximum 360°C Duration: maximum 3 sec.

We highly recommend that you confirm your actual solder conditions

### 3. Moisture Sensitivity

Moisture Sensitivity Level standard is not applicable to electromechanical realys.

#### 4. Tin Whisker

 Dipped SnAgCu solder is known as low risk tin whisker. No considerable length whisker was found by our in house test.

#### **Fujitsu Components International Headquarter Offices**

Japan

Fujitsu Component Limited Gotanda-Chuo Building

3-5, Higashigotanda 2-chome, Shinagawa-ku

Tokyo 141, Japan Tel: (81-3) 5449-7010 Fax: (81-3) 5449-2626

Email: promothq@ft.ed.fujitsu.com

Web: www.fcl.fujitsu.com

North and South America

Fujitsu Components America, Inc. 250 E. Caribbean Drive Sunnyvale, CA 94089 U.S.A. Tel: (1-408) 745-4900

Fax: (1-408) 745-4970 Email: marcom@fcai.fujitsu.com

Web: http://www.fujitsu.com/us/services/edevices/components/

Europe

Fujitsu Components Europe B.V.

Diamantlaan 25 2132 WV Hoofddorp Netherlands

Tel: (31-23) 5560910 Fax: (31-23) 5560950 Email: info@fceu.fujitsu.com

Web: http://www.fujitsu.com/emea/services/components/

Asia Pacific

Fujitsu Components Asia Ltd. 102E Pasir Panjang Road #04-01 Citilink Warehouse Complex

Singapore 118529 Tel: (65) 6375-8560 Fax: (65) 6273-3021 Email: fcal@fcal.fujitsu.com

Web: http://www.fujitsu.com/sg/services/micro/components/

©2005 Fujitsu Components America, Inc. All rights reserved. All trademarks or registered trademarks are the property off their respective owners.

Fujitsu Components America does not warrant that the content of datasheet is error free. In a continuing effort to improve our products Fujitsu Components America, Inc. reserves the right to change specifications/datasheets without prior notice. Rev. 11/08/2005.