

CAT. N° 4 121 63

**SINGLE PHASE SPLIT CORE CT - FOR 50 X 80 MM BAR -
TRANSF RATIO 800/5**


| | |
|---------------------------|----------|
| Pack (number of units) | 1 |
| Volume (dm ³) | 1,561 |
| Weight (g) | 1 040,00 |

Product characteristics**Single-phase split-core current transformers**

- Used with ammeters, electricity meters or multi-function measuring units
- Current at the secondary: 5 A
- For fixing directly on bars
- Secondary connected by terminals or lugs
- Precision class: 0,5 %

For 50 x 80 mm bar

- Transformation ratio : 750/5
- Output : 3 VA

General characteristics**Current transformers (CT)****Documentation** **Catalogue pages & additional information**

- [Description page \(p.106\)](#)
- [Current transformers \(CT\)](#)

 **Installation & technical data**

- [F01961EN-02](#)