

CAT. N° 4 121 68



SINGLE PHASE SPLIT CORE CT - FOR 80 X 160 MM BAR - TRANSF RATIO 3000/5

Pack (number of units)	1
Volume (dm ³)	7,951
Weight (g)	2 820,00

Product characteristics

Single-phase split-core current transformers

- Used with ammeters, electricity meters or multi-function measuring units
- Current at the secondary: 5 A
- For fixing directly on bars
- Secondary connected by terminals or lugs
- Precision class: 0,5 %

For 80 x 160 mm bar

- Transformation ratio : 3000/5
- Output : 20 VA

General characteristics

Current transformers (CT)

Documentation



Catalogue pages & additional information

- [Description page \(p.106\)](#)
- [Current transformers \(CT\)](#)



Installation & technical data

- [F01961EN-02](#)